



# SSP1500SS AVR

powered by Honda GX 690

## Model SSP1500SS - AVR



Preliminary  
for information only




### 1. General Details

Frequency	50 Hz	
Voltage	230 V	
Max Power	11	KVA
Continuous power	10	KVA
Power factor cos $\phi$	0,8	
Max Power	8,8	KWe
Continuous power	9	KWe

### 2. Petrol driven engine

Make and model	<b>Honda</b>	<b>GX690</b>
rpm	3000	
Max power at 3600 rpm	22,1	HP
Cooling system	Air	
Cylinders	2	
Displacement (cm <sup>3</sup> )	688	



3. Alternator						
Make and model	LINZ		E1S11MB KE KVA			
Max power	Kva 11					
4. Starting system						
Electric						
5. Standard Equipment						
<ul style="list-style-type: none"> <li>✓ Soundproof canopy</li> <li>✓ Vibration dampers</li> <li>✓ Low oil level protection</li> <li>✓ Exhaust gas silencer</li> </ul>		<ul style="list-style-type: none"> <li>✓ Air filter</li> <li>✓ Integrated fuel tank</li> <li>✓ Distribution control panel with output sockets with circuit breaker</li> <li>✓ Manual control panel QM107</li> <li>✓ Lifting eye</li> </ul>				
6. Electric Panels						
<b>QM 107 STANDARD</b>			<b>ACP 0411</b> available for genset with electronic starting system			
 <ul style="list-style-type: none"> <li>✓ Starter key</li> <li>✓ 16A Single Phase socket 3P</li> <li>✓ 32A Single phase socket 3P</li> <li>✓ Circuit breaker</li> <li>✓ Power Terminal Board</li> <li>✓ Emergency stop button</li> <li>✓ Hour counter</li> <li>✓ Voltmeter, frequencymeter</li> <li>✓ Fuel warning light</li> </ul>			 <ul style="list-style-type: none"> <li>✓ Control unit</li> <li>✓ Frequency and voltage indicators</li> <li>✓ Generating set/mains supply contractors</li> <li>✓ Automatic battery charger</li> </ul>			
7. Logistic Information						
	Model	Fuel tank (litres)	Weight (Kgs)	Dimensions (cm)		
				L	W	H
	Silent Star P SSP15000SS	20	210	107	56	93
8. Fuel consumption						
litres/hour at 75% load		7	approx			
9. Marking						
Label showing the general data of the genset (voltage, power, frequency). engine model with serial number, alternator model. W.F.M LOGO						
10. Operating manuals						
English. Other languages available on request.						