

# GENMAC Infinity-Rent G15KS-M5 GENERATOR 15,4KVA



## Product description:

GENMAC Infinity-Rent G15KS-M5 THREE-PHASE GENERATOR 15,4KVA

The generator GENMAC Infinity-Rent G15KS-M5 three-phase is equipped with a Kohler diesel-powered engine capable of delivering a power of 15,4KVA with AVR voltage regulator.

The generator is equipped with an oversized Kohler engine capable of delivering a continuous power of 14.4KVA and a maximum power of 15,4KVA. Thanks to the 50l tank the Genmac Infinity generator has an autonomy of up to 14 hours of work.

The Genmac generator silenced has been realized with a high performance frame to minimize the sound pressure. The frame is made with steel plates made according to UNI S235JR standards, complete with rubber anti-vibration supports. In order to improve the handling before use, at the base of the generator there are bilateral steel pockets for forklift trucks, which allows lifting from all sides, and on the top of the generator there is a hook for central lifting.

The 15,4KVA generator is complete with 4 doors that allow easy access for ordinary or extraordinary maintenance. In order to make this Genmac generator as quiet as possible, 100% recyclable, fireproof, self-extinguishing, fireproof, washable, class 1 reaction to fire, mechanically fixed to the frame.

The Genmac Infinity-Rent silenced generator specific for mobile and rental applications. Easy to use and move. It mounts the latest generation engine with low emissions, for energy that respects the environment.

## Control Panel

The control panel is composed as follows:

No. 1 CEE 32A 400V

No. 1 CEE 16A 400V



No. 2 CEE 16A 230V  
No. 1 Schuko 16A 230V  
Thermal switch  
Magnetothermal switch  
DSE4510 control panel

- Generator power reading (kW, kV Ar, kV A & pf)
- Overload Protection (kW & kV Ar)
- Low Oil Pressure Protection
- High Coolant Temperature Protection
- Low Fuel Level Protection
- Alternator Battery Charging Failure
- Overspeed Protections
- Oil Pressure and Engine Temperature Readout

Fuel Level Analog Instrument  
Emergency Stop Button  
Remote Start/Auto Panel Connector  
On/Off Switch

#### AVR Voltage Regulator

The AVR is essential to make the generator work at its best, in fact it all needs an electronic control system, an AVR in fact, which ensures the proper functioning of the machine and the electrical network behind it.

The purpose of the AVR, in a current generator, is to keep the output stable. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed phase shift current counteracts the inductor magnetic field, causing a voltage drop at the alternator terminals; to compensate for this phenomenon, the AVR intervenes automatically by increasing the excitation current, until the returns to the nominal value. If the load is capacitive, the current acts as a magnetizer for the inductor causing an increase in voltage exit, and the AVR intervenes by reducing the excitation current.

#### TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Infinity-Rent G15KS-M5 15,4KVA

Phase Type: SinglePhase / ThreePhase  
SinglePhase Continuous Power: 4.8KVA / 3.8KW  
SinglePhase Maximum Power: 5.1KVA / 4.1KW  
ThreePhase Continuous Power: 14.4KVA / 11.5KW  
ThreePhase Maximum Power: 15.4KVA / 12.3KW  
Motor: Kohler KDW1603  
Emissions Standard: Stage V  
Starting: Electric  
Power Supply: Diesel  
Receptacle Panel: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V



Voltage: 230 / 400 V  
Frequency: 50 Hz  
Motor RPM: 1500 rpm  
Tank Capacity: 50 l  
Autonomy @ 75%: 14 h fixed revolutions  
Voltage regulator: AVR  
Sound pressure @7m: 67 dBa  
Length (mm): 1802  
Width (mm): 752  
Height (mm): 1130  
Dry weight (Kg): 558

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

**Product features:**

Phase: Single phase / Three phase  
Maximum power single phase (KW): 4.1  
Continuous power single phase (KW): 3.8  
Maximum power single phase (KVA): 5.1  
Continuous power single phase (KVA): 4.8  
Maximum power three phase (KW): 12.3  
Continuous power three phase (KW): 11.5  
Maximum power three phase (KVA): 15.4  
Continuous power three phase (KVA): 14.4  
Fuel: Diesel  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V  
Engine: Kohler KDW1603  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 1500  
Starting system: Electric  
Cooling: Water  
Poles: 2  
Fuel tank capacity (L): 50  
Running time (h): 14  
Acoustic pressure: 67 dB(A) at 7 m  
Length (mm): 1802  
Width (mm): 752

---

Height (mm): 1130  
Dry weight (Kg): 558  
Silenced: Yes  
Super silenced: Yes  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Kohler