

## S12000 230V 50HZ #CONN

THE COMPLETE PETROL PACKAGE



S 12000 has an exceptional quality and strength. It responds to all EEC markets requirements and it's a rare product, with such power, to complying with the EU regulations on noise emission (2000/14/CE). S 12000 offers all the features of a top class product: A powerful and economical engine, a strong and modern design and a long-run easy filling fuel tank. Perfect for intensive use, this generator is equipped with a control panel which allows to integrate many accessories and options for better confort and for optimal command.

### Main Features

Frequency	Hz	50
Voltage	V	230
Power factor	cos $\phi$	0.9
Phase and connection		1

### Power Rating

Standby power LTP	kVA	11.9
Standby power LTP	kW	10.7
Continuous power COP	kVA	10.0
Continuous power COP	kW	9.1

#### Ratings definition (According to standard ISO8528 1:2005)

**COP** - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

**LTP** - Limited-Time running Power: It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

### Engine specifications

Engine manufacturer		Honda
Model		GX630
Engine cooling system		Air
Displacement	cm <sup>3</sup>	688
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Petrol
Oil capacity	l	1.9
Starting system		Electric

### Alternator Specifications

Class		H
Voltage regulation system		Capacitor
IP protection		23
Poles		2
Frequency	Hz	50

### Dimensional data

Length	(L) mm	960
Width	(W) mm	641
Height	(H) mm	667
Dry weight	Kg	162
Fuel tank capacity	l	24

### Autonomy

Running time @ 75% PRP	h	5.67
Running time @ 100% PRP	h	4.26

### Noise level

Guaranteed noise level (LWA)	dB(A)	96
Noise pressure level @ 4 mt	dB(A)	72



## GENSET CONTROL PANELS (CONN)

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.



### Commands:

- Start selector switch with key: OFF - ON - START
- Pushbutton Choke
- CONNector for AMF/RSS (Accessory available)

### Protections:

- Magneto Thermal Protection
- Oil Guard

### SOCKET TYPE

SCHUKO 230V 16A IP54	1
2P+T CEE 230V 16A IP44	1
2P+T CEE 230V 32A IP44	1

## ACCESSORIES CONTROL PANEL

### **AMF - AUTOMATIC CONTROL PANEL (CONN)**

This accessory permits to control all the functions about a generator. It's built to monitor mono phase or three phase with neutral systems in alternate current; it permits to transfer the user's load on generator when the mains voltage is faulty. Conversely, as soon as AMF system detects the power grid, it stops the generator.

#### **Equipment:**

- Control and protection unit (DGT)
- Phase detector
- Contactor with interblock
- Battery charged
- Acoustic alarm
- 8 meters control wiring (with CONNector)
- External start stop capability
- Emergency stop button

#### **Instrumentation (DGT):**

- Mains voltage
- Genset voltage
- Frequency meter
- Hour meter

#### **Alarm & Shutdowns:**

- Generators voltage out of limits
- Battery Voltage out of limits
- Low oil Pressure
- Fail to start
- External shutdown

### **RSS - REMOTE START / STOP (CONN)**

RSS Remote start/stop wireless with CONNector (max Distance 90m)



## ACCESSORIES

### TRANSPORTATION KIT

- With fix handles
- With folding handles



### LIGHT TOWER

for portable generators (with tubular frames)

- Maximum Height 4.2m
- Elevations Pneumatic
- Quick open/close systems for legs
- Mast support and four lifting
- Lamp available Watt/Type:
  - n.4 X 500W Halogen (required power from generator: 2.5kVA 230V Single Phase)
  - n.4 X 1000W Halogen (required power from generator: 5,0kVA 230V Single Phase)



### MTS- MANUAL TRANSFER SWITCH

- Manual transfer switch 40A (for manual control versions 230V)

