

MPL 180 S-I



MASE GENERATORS S.p.A. Via Tortona, 345 47522 Cesena (FC) Italy Tel.+39-0547-354311 Fax.+39-0547-317555 Email: mase@masegenerators.com







MPL 180 S-I

SILENCED THREE-PHASE POWER GENERATOR / OUTPUT POWER 176 KVA THREE-PHASE AND 58,6 KVA SINGLE-PHASE / DIESEL ENGINE 1500 RPM

Gen Set Features

+ Controller with digital display for full monitoring of generator parameters: 3-phase generator voltage, 3-phase mains voltage, battery voltage, ammeter, frequency, hour meter, oil pressure, engine temperature, fuel level, fail to start;

with auto engine protection shutdown system in case of:

- fail to startemergency stop
- low oil pressurelow fuel level
- high coolant temperature

- + 4 poles main circuit breaker
- + Three-phase output terminal board
- + Emergency STOP button
- + Automatic Voltage Regulator
- + Manual oil sump pump
- + Fork-lift pockets
- + Remote control terminal board
- + ATS terminal board

Gen Set Options

(available as factory options)

+ 60 Hz version

- + Versions with different voltages + Automatic Frequency Regulator
- + Engine water heaters powered by mains 230 V 50 Hz

Accessories on Request

- + Remote Start/Stop kit by cable (20/50 m)
- + Auto Transfer Switch (ATS) panel complete with battery charger for auto-start operation

Noise Level

+ Lwa 97

(72 dB a 7 m)

AC Generator 50 Hz

- + Type: synchronous
- + Three-phase power (stand by): 176 kVA 400 V
- + Three-phase power (prime): 160 kVA 400 V
- + Single-phase power (max.): 58,6 kVA 230 V
- + Power Factor: cosφ 0,8

Diesel Engine 1500 rpm

- + Type: Iveco NEF67TM3A turbocharged 6 cyl. 212,6 HP (156,4 kWm) 6700 cm³
- + Fuel: diesel
- + Cooling system: water
- + Starting system: electric
- + Fuel tank capacity: 230 l
- + Fuel consumption @ 75%: 29 l/h

Other Features

- + Insulation Class: H
- + Ambient temperature: 40 °C (*)
- + Altitude: 1000 mt (*)
- + Mechanical Protection: IP 23
- + Dimensions (L x W x H): 3300 x 1100 x 1650 mm
- + Dry weight: 2000 kg
- (*) For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.