

## Fischer Panda "Compact Power" 1500/1800 series

Suitable for heavier commercial applications or more than 2000 operating hours per year

Panda 1500/1800 rpm series marine generators with voltage regulation and voltage tolerance  $\pm 3V$

- 1500 rpm - 50 Hz - 230 V
- 1500 rpm - 50 Hz - 400 V
- 1800 rpm - 60 Hz - 120 / 240 V
- 1800 rpm - 60 Hz - 208 V AC

		Panda 7.5-4 PMS	Panda 9-4 PMS	Panda 12-4 PMS	Panda 22-4 PMS	Panda 30-4 PMS
<b>230V</b>	kW	6.5	8.0	10.5	18.6	25.5
	kVA	7.6	9.4	12.3	21.9	30
<b>400V</b>	kW	6.5	8.0	10.5	18.6	25.5
	kVA	7.6	9.4	12.3	21.9	30
<b>120 V</b> (on request : 2 x 120 V / 240 V)	kW		(9.6)	(12.6)	(22.3)	(30)
	kVA		(11.3)	(14.8)	(22.3)	(30)
<b>208 V</b>	kW		(9.6)	(12.6)	(22.3)	
	kVA		(11.3)	(14.8)	(22.3)	
		1500 / (1800)	1500 / (1800)	1500 / (1800)	1500 / (1800)	1500 / (1800)
		$\pm 3 V$	$\pm 3 V$	$\pm 3 V$	$\pm 3 V$	$\pm 3 V$
		VCS	VCS	VCS	VCS	VCS
		2	2	2	2	2
		GRP	GRP	GRP	MPL	MPL
Sound insulation		3D	3D	3D	4DS	4DS
		Kubota	Kubota	Kubota	Kubota	Mitsubishi
		D1105	D1105	V1505	V2403M	S4S
		1123	1123	1498	2434	3331
		3	3	3	4	4
dbA		52 / 62 / 66	52 / 62 / 66	52 / 62 / 66	53 / 63 / 67	
mm		830 515 627	830 515 627	950 515 670	1255 720 770	1280 740 830
kg		278	280	315	610	720

The data in this publication reflects the technical state at time of print. Due to our policy of continual product development, we reserve the right to alter technical specifications without notice. Dimensions apply for the sound insulation capsule only and do not include latches, fittings etc. Additional room will need to be calculated for the installation to include hoses, cables and capsule mountings. Please confirm current dimensions and weights when ordering.