

# GAMMA-GAS G85GO-NG

50Hz@1500RPM 400/230V 3PH

**GENMAC**  
POWER PRODUCTS



Picture for illustration purposes only

## General features

Open generator with following specifications:

### Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR
- Heavy duty, bell type, rubber anti-vibration mountings
- Dedicated area to make easier the electrical connection to the load
- Easy access to fuel refilling
- Feet and four lifting holes on the base

### Muffler:

- Industrial type
- With aluminum coating

### Control Panel:

- Self-standing control panel tower made with metal structure and components to grant IP65 protection, easily removable for maintenance
- Control panel is divided in two independent and insulated boxes separating Controls (Controller and numbered terminal board) from Power connection (circuit breaker and cable inlet)
- External dedicated area to make easier the electrical connection to the load
- Power connection between circuit breaker and alternator made with high resistance neoprene cables (H07RNF) and using cable glands for waterproof connections

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

## Overall performance

### G85GO-NG

PRP Continuous power kVA	79
PRP Continuous power kW	63
LTP Stand-by power kVA	93
LTP stand-by power kW	75
Power factor cos $\phi$ ip	0.8
Voltage VAC	400/230
Frecuency Hz	50
Ampere PRP/LTP	114 / 135
Speed RPM	1500

## Dimensions and noise level

Length mm	2250
Width mm	1020
Height mm	1521
Net Weight kg	1145
Gross Weight kg	-
Sound pressure at 7 mt dBA	-

## Data reference

Standard reference conditions temperature 25°C, altitude 100m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer. according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1.The number of hours per year is stated by the Manufacturer. Overload is not permitted.\*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery.

# GAMMA-GAS G85GO-NG

50Hz@1500RPM 400/230V 3PH

**GENMAC**  
POWER PRODUCTS

## Engine general data

Engine brand	<b>GM General Motors</b>
Model	<b>RMG8000-D01-01</b>
PRP Power kW	<b>83.00</b>
LTP Power kW	<b>91.30</b>
Fuel	<b>Natural gas</b>
Nr. cylinders	<b>8</b>
Air intake	<b>Aspirated</b>
Cooling	<b>Water</b>
Cubic capacity l.	<b>8.00</b>
Speed regulation	<b>Electronic</b>
Regulator precision +/-%	<b>- - -</b>
Voltage VDC	<b>12</b>
Emissions	<b>-</b>

## Fuel consumption

Consumo 25% m <sup>3</sup> /h	<b>10.50</b>
Consumo 50% m <sup>3</sup> /h	<b>15.80</b>
Consumo 75% m <sup>3</sup> /h	<b>22.20</b>
Consumo 100% m <sup>3</sup> /h	<b>28.40</b>
Autonomy at 75% of load h.	

## Engine liquids and equipment

Type of lubricant	<b>Oil SAE 15W40</b>
Lubrication capacity l.*	<b>7.60</b>
Type of coolant	<b>Antifreeze liquid</b>
Coolant capacity l.*	<b>31.20</b>
Air intake filter	<b>Paper cartridge</b>
Battery capacity Ah	<b>100</b>
Number of batteries*	<b>1</b>

## Alternator general data

Alternator brand	<b>Mecc-Alte</b>
Model	<b>ECP34-1S/4A</b>
Type of excitation	<b>Self-excited</b>
Type of regulation	<b>AVR</b>
Regulator precision +/-%	<b>1.00</b>

## Fuel system and energy balance

Gas supply pressure mbar	<b>-</b>
Combustion air flow volume LTP m <sup>3</sup> /min	<b>-</b>
Cooling air capacity LTP m <sup>3</sup> /min	<b>-</b>
Exhaust gas flow-density LTP m <sup>3</sup> /min	<b>13.80</b>
Exhaust gas temperature LTP °C	<b>599.00</b>
Brake mean effective pressure kPa	<b>-</b>
Energy to exhaust LTP kWt	<b>-</b>
Energy to coolant LTP kWt	<b>-</b>
Energy to radiation LTP kWt	<b>-</b>

## Structure data

Type of structure	<b>GAMMA-GAS</b>
Tank capacity l.	<b>-</b>
Retention basin	<b>yes</b>
Exhaust diameter mm	<b>120</b>

## Control panel features

### QT2A-4520

Self-standing tower with IP65 metal box  
Circuit breaker  
AMF controller DSE4520  
- Voltmeter, Frequency meter, Ammeter  
- Generator power (kW, kV Ar, kV A & pf) monitoring  
- Hour meter  
- Fuel level meter  
- Overload (kW & kV Ar) protection  
- Low oil pressure protection  
- High coolant temperature protection  
- Low fuel level protection  
- Battery charger alternator fault  
- Rpm protection  
Emergency stop button  
Audible alarm  
Terminal board for ATS connection  
Can Bus reading Port (if standard on the engine)  
Battery charger  
On/off switch



Dealer