

MG 11.5 DTK



Control panel



1500 rpm Kubota engine



Fuel inlet and outlet



Stage V

We offer now what others will do tomorrow.



GenSet s.p.a.

Via Stazione 5 - 27030
Villanova d'Ardenghi (PV) - Italy
Phone: +39-0382-5091

commerciale@genset.it
www.genset.it

 **GenSet**
Next Gen technology
for top business.

VEHICULAR GENERATOR

OUTPUT POWER 10 kVA THREE-PHASE AND 3,3 kVA SINGLE-PHASE

KUBOTA DIESEL ENGINE 1500 RPM

SUPER-SILENCED VERSION

Standard Features

- Remote control panel with: multifunction display showing single-phase generator voltage, battery voltage, frequency, hour meter, rpm
- Built-in control panel
- Start / Stop button
- Connection cable to remote panel
- Safety shutdown in case of: low oil level, high water temperature
- Engine failure warning lights
- Operation lamp
- Hourmeter
- Circuit breaker for the generator protection
- General shutdown switch
- Faults memory
- External muffler

Options

available as factory options

- 20 lt plastic fuel tank with brackets
- 20 lt steel fuel tank with brackets
- Fuel reserve indicator kit
- Fuel filler with key lock cap
- 1 mt fuel pipe for connection tank-fuel filler
- Fuel pipe I/O to the automatic tank
- CBU remote control panel with 20 mt cable

Noise level

- Lwa 83 (58 dB a 7 mt)

AC generator - 50Hz

- Type: synchronous
- Three-phase power (max.): 10 kVA - 400V
- Single-phase power (max.): 3,3 kVA - 230V
- Power Factor: $\cos \phi$ 0,8

**Diesel Engine
1500 rpm**

- Type: Kubota D1105 - 3 cyl. - 12,7 hp (9,5 kWm) - 1123 cm³
- Cooling system: water
- Starting system: electric
- Fuel consumption @ 75%: 2 lt/h

Other features

- Insulation Class: H
- Ambient temperature: 40 °C (*)
- Altitude: 1000 mt (*)
- Mechanical Protection: IP 23
- Dimensions (L x W x H): 1070 x 560 x 660 mm
- Dry weight: 320 kg

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.
In line with our continued development, innovation and voice of customer program, we reserve the right to change data without notice.