



GENMAC QUEEN-GAS G60GS-LPG THREE- PHASE GENERATOR 61 KVA LPG GAS - STAMFORD ALTERNATOR

Product description:

GENMAC QUEEN-GAS G60GS-LPG

The GENMAC QUEEN-GAS G60GS-LPG is a 61 KVA super-silenced single-phase/three-phase LPG generator set with Stamford alternator and AVR voltage regulator.

Thanks to its LPG gas fuel supply, the GENMAC QUEEN-GAS G60GS-LPG can only consume 26.3 Lt/h at full load and has a low environmental impact, making it one of the best in its class.

The long life and reliability of the GENMAC QUEEN-GAS G60GS-LPG is due to a special control procedure during the various stages of production.

The GENMAC QUEEN-GAS G60GS-LPG is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

Not binding images and technical data.

Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 54

Continuous power three phase (KW): 48

Maximum power three phase (KVA): 67

Continuous power three phase (KVA): 61

Fuel: LPG

Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: Terminal box
Engine: General Motors RMG5700-D51-01
Emissions Regulations: Stationary Use
Engine rpm (rpm): 1500
Speed governor: Electronic
Starting system: Electric
Engine capacity (cm³): 5700
Number cylinders: 8
Oil capacity (L): 4.7
Cooling: Water
Alternator: Stamford S1L2-Y1, self-excited
Poles: 4
LPG consumption (L/h): 26.3
Width (mm): 1056
Height (mm): 1900
Dry weight (Kg): 1359
Silenced: Yes
Super silenced: Yes
Product type: Generator
ATS Switch device : No
Voltage regulator: AVR
Engine manufacturer: General Motors