



# CGM C7000T



Product price:

**1.477,50 € tax excluded**

## Product description:

Generator CGM C7000T Three-phase 7 KVA

CGM C7000T single/threephase 7 KVA generator set with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers.

The CGM C7000T generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM C7000T generator set is equipped with manual recoil starter with recoil starter and low fuel consumption, in fact it consumes only 2 litres/hour at 75% of the load. This CGM C7000T generator set is perfect for outdoor use such as hobby use.

The CGM C7000T generator set is part of the CLASSIC series and is easily adaptable to a variety of uses such as homes, street installations, camping sites, hobbies, construction sites, etc.. The CGM C7000T at 3000 rpm is only suitable for emergency use. We do not recommend use for more than 6 consecutive hours and more than 500 hours per year.

## Technical characteristics of the CGM C7000T:

Type of phase: Singlephase / Threephase  
Maximum singlephase power: 2.6 KVA / 2 KW  
Continuous singlephase power: 2.3 KVA / 1.8 KW  
Maximum threephase power: 7.7 KVA / 6.1 KW  
Continuous threephase power: 7 KVA / 5.6 KW  
Fuel: Petrol  
Voltage: 230/400 V  
Frequency: 50 Hz  
Motor: HONDA GX390  
Engine rpm: 3000 rpm  
Starting: Manual



Voltage regulator system: AVR  
Consumption: 2 Lt / h at 75% of the load  
Tank capacity: 6.1 Lt  
Autonomy: 3 h at 75% of the load  
Length: 780 mm  
Width: 510 mm  
Height: 500 mm  
Weight: 75 Kg

Discover the full range of generators from CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

**Product features:**

Phase: Single phase / Three phase  
Maximum power single phase (KW): 2  
Continuous power single phase (KW): 1.8  
Maximum power single phase (KVA): 2.6  
Continuous power single phase (KVA): 2.3  
Maximum power three phase (KW): 6.1  
Continuous power three phase (KW): 5.6  
Maximum power three phase (KVA): 7.7  
Continuous power three phase (KVA): 7  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE  
Engine: Honda GX390  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Manual  
Engine capacity (cm<sup>3</sup>): 389  
Number cylinders: 1  
Alternator: Made in Italy  
Poles: 2  
Fuel tank capacity (L): 6.1  
Consumption (L/h): 2  
Running time (h): 3  
Length (mm): 780

---

Width (mm): 510  
Height (mm): 500  
Dry weight (Kg): 75  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Honda