



# CGM CX5000TE



**Product price:**

**1.875,00 € tax excluded**

## **Product description:**

Generator Three-phase CGM CX5000TE 5KVA AVR

Generator Three-phase CGM CX5000TE 5KVA with Honda engine powered by STAGE V gasoline at 3000 rpm, compact and easy to use, mounted on a fixed base with sturdy rain cover and vibration dampers. The CGM CX5000TE generator set is composed of a Made in Italy Linz or NSM alternator, self-excited with brushes and with an AVR regulator. The AVR regulator allows to stabilize the voltage and does not ruin the connected sensitive devices. The CGM CX5000TE generator set is equipped with electric start but also with manual recoil start and with a low fuel consumption, in fact it consumes only 1,6 liters/hour at 75% of the load. This CX5000TE generator set is perfect for outdoor use such as for hobby use. The CGM CX5000TE generator is part of the DELUXE series and is easily adaptable to various uses such as homes, mobile homes, campsites, hobbies, construction sites, etc.. The CX5000TE generator set at 3000 rpm is suitable for emergency use only. It is not recommended to be used for more than 6 hours continuously and for more than 500 hours per year.

## **Technical specifications of CGM CX5000TE generator set:**

Type of phase: Singlephase / Threephase

Maximum singlephase power: 1.8 KVA / 1.6 KW

Continuous singlephase power: 1.6 KVA / 1.3 KW

Maximum threephase power: 5.5 KVA / 4.8 KW

Continuous threephase power: 5 KVA / 4 KW

Fuel: Petrol

Voltage: 230/400 V

Frequency: 50 Hz

Motor: HONDA GX270

Engine rpm: 3000 rpm

Starting: Electric



Voltage regulator system: AVR  
Consumption: 1.6 Lt / h at 75% of load  
Tank capacity: 15 Lt  
Autonomy: 9.4 h at 75% of the load  
Length: 825 mm  
Width: 550 mm  
Height: 530 mm  
Weight: 78 Kg

Discover the full range reserved for terrestrial generator sets of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data are not binding.

**Product features:**

Phase: Single phase / Three phase  
Maximum power single phase (KW): 1.6  
Continuous power single phase (KW): 1.3  
Maximum power single phase (KVA): 1.8  
Continuous power single phase (KVA): 1.6  
Maximum power three phase (KW): 4.8  
Continuous power three phase (KW): 4  
Maximum power three phase (KVA): 5.5  
Continuous power three phase (KVA): 5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO  
Engine: Honda GX270  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 270  
Number cylinders: 1  
Alternator: Made in Italy  
Poles: 2  
Fuel tank capacity (L): 15  
Consumption (L/h): 1.6

Running time (h): 9.4

Length (mm): 825

Width (mm): 550

Height (mm): 530

Dry weight (Kg): 78

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda