



# CGM CX7000TE



Product price:

**2.212,50 € tax excluded**

## Product description:

Generator CGM CX7000TE Three-phase 7KVA AVR

Generator CGM CX7000TE Three phase 7KVA with Honda engine powered by STAGE V petrol at 3000 rpm, compact and easy to use, mounted on a fixed base with vibration dampers. The CGM CX7000TE generator set consists of a Made in Italy alternator from Linz or NSM, self-excited with brushes and with AVR voltage regulator. The CGM CX7000TE generator set is equipped with electric starter and low fuel consumption, in fact it consumes only 2 litres/hour at 75% of the load. This CX7000TE generator set is perfect for outdoor use such as hobby use.

The CGM CX7000TE generator set is part of the DELUXE series and is easily adaptable to a variety of uses such as homes, street installations, camping, hobbies, construction sites, etc.. The CX7000TE generator set at 3000 rpm is only suitable for emergency use. It is not recommended to use it for more than 6 hours continuously and for more than 500 hours per year.

## Technical characteristics of the CGM CX7000TE generator:

Type of phase: Singlephase / Threephase

Maximum singlephase power: 2.5 KVA / 2 KW

Continuous singlephase power: 2.3 KVA / 1.8 KW

Maximum threephase power: 7.7 KVA / 6.1 KW

Continuous threephase power: 7 KVA / 5.6 KW

Fuel: Petrol

Voltage: 230 V / 400 V

Frequency: 50 Hz

Engine: HONDA GX390

Engine revs: 3000 rpm

Starting: Electric

Voltage regulator system: AVR

Consumption: 2 Lt/h at 75% of the load

Tank capacity: 15 Lt





Autonomy: 7.5 h at 75% of the load

Length: 825 mm

Width: 550 mm

Height: 530 mm

Weight: 85 Kg

Discover the entire range reserved for generators of CGM or other top brands by browsing our catalog to find the one that best suits your needs.

Images and technical data not binding.

### Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2

Continuous power single phase (KW): 1.8

Maximum power single phase (KVA): 2.5

Continuous power single phase (KVA): 2.3

Maximum power three phase (KW): 6.1

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 7.7

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 5P CEE - 1 x 230V 16A 3P CEE - 1 x 230V SCHUKO

Engine: Honda GX390

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 389

Number cylinders: 1

Alternator: Made in Italy

Poles: 2

Fuel tank capacity (L): 15

Consumption (L/h): 2

Running time (h): 7.5

Length (mm): 825

Width (mm): 550

Height (mm): 530

Dry weight (Kg): 85



Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda