



GENMAC Combipro G7900HC-M5 GENERATOR 8,0KVA

Product price:

1.736,00 € tax excluded

Product description:

GENMAC COMBIPRO G7900HC-M5 THREE-PHASE GENERATOR 8,0KVA

The generator Genmac Combipro G7900HC-M5 Single/ Three phase is equipped with a Honda gasoline powered engine capable of delivering a power of 8,0KVA with capacitor voltage regulator (AVR optional).

The Generators of the **Genmac Combipro G7900 series** are among the most **silent** in their category, thanks to the side closing panels and the oversized muffler.

The front panel of the Genmac 8,0KVA generator is protected by a canopy and is complete with a back panel that guarantees protection and insulation from water. The generator is equipped with electric starter and injection engine with electronic speed regulation.

The Genmac G7900 8,0KVA generators are equipped with a **25-liter tank** with a large cap that is convenient to unscrew even with work gloves, filter and **fuel level indicator**. There is also a manual fuel circuit shut-off tap to prevent fuel leakage.

The Genmac Combipro mounts a **Honda OHV 4-stroke petrol engine**. They are very reliable engines that guarantee efficient combustion and **low fuel consumption**. The engines with 8,0KVA generators are also equipped with a protection system that causes the **engine to stop if the oil level is too low**.

The 8,0KVA generator with capacitor voltage regulator, on request it can be supplied with AVR.

AVR Voltage Regulator

All models in the Genmac Combipro series are available with optional AVR regulator. The AVR is a device that allows to **maintain the output more constant and less load-dependent**. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various



devices connected, improving their performance and durability.

The model equipped with AVR card is highly recommended, as it guarantees a significant improvement in the stability of the output voltage; this feature makes the generators particularly suitable with common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you can enjoy greater stability and thus increase the life of your devices.

TECHNICAL FEATURES OF GENERATOR GENMAC COMBIPRO G7900HC-M5

Voltage regulator : capacitor (AVR Optional)

Power supply: Gasoline

Starting: Manual

Phase type: Singlephase / Threephase

Singlephase continuous output: 2.4KVA / 2.2KW

Maximum singlephase output: 2.6KVA / 2.4KW

Threephase continuous output: 7.3KVA / 5.8KW

Threephase maximum output: 8,0KVA / 6.4KW

Motor: Honda GX390

Socket panel: 1 x schuko 230V - 1 x 16A 230V - 1 x 16A 400 V

Emission standard: Stage V

Voltage: 230 / 400V

Frequency: 50 Hz

3000 rpm

Tank: 25 Lt.

Autonomy @ 75%: 12 h fixed rpm

Boosting: Manual

Length (mm): 800

Width (mm): 640

Height (mm): 700

Dry weight (Kg): 106

If you are looking for another product then you can see on our catalog other Generator

Images and technical data not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2.4

Continuous power single phase (KW): 2.2

Maximum power single phase (KVA): 2.6

Continuous power single phase (KVA): 2.4

Maximum power three phase (KW): 6.4

Continuous power three phase (KW): 5.8

Maximum power three phase (KVA): 8

Continuous power three phase (KVA): 7.3

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Honda GX390

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Starting system: Manual

Cooling: Air

Poles: 2

Fuel tank capacity (L): 25

Running time (h): 12

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 800

Width (mm): 640

Height (mm): 700

Dry weight (Kg): 106

Silenced: Yes

Super silenced: No

ATS Switch device : No

Voltage regulator: AVR (optional)

Engine manufacturer: Honda