



# GENMAC Urban-Rent G15000KS-M5 GENERATOR 15,0KVA

**Product price:**

**6.701,00 € tax excluded**

## **Product description:**

GENMAC Urban-Rent G15000KS-M5 THREE-PHASE GENERATOR 15,0KVA

The generator GENMAC Urban-Rent G15000KS-M5 three-phase is equipped with a Kohler diesel-powered engine capable of delivering a power of 15,0KVA **with AVR** voltage regulator.

The high quality professional silenced diesel generator of the construction series, Genmac Urban-Rent with power of 15,0KVA, produced by Italian company Genmac. The generator is equipped with an oversized engine with water cooling and a practical electric starter.

For this line of generators is possible the supply of a differential protection circuit, in addition is possible the supply of trolleys for the handling of the unit.

The Genmac Urban-Rent silenced generator specific for mobile and rental applications. Easy to use and move. It mounts the latest generation engine with low emissions, for energy that respects the environment.

Genmac 15,0KVA generators are highly reliable machines, built with quality components to be used in professional field, where reliability is fundamental.

Genmac generators are supplied with AVR card, tank with collection tank and central lifting hook as standard on all models.

## Control Panel

The control panel is composed as follows:

No. 1 CEE 32A 400V

No. 1 CEE 16A 400V

No. 2 CEE 16A 230V

No. 1 Schuko 16A 230V



Thermal switch

Magnetothermal switch

DSE4510 control panel

- Generator power reading (kW, kV Ar, kV A & pf)
- Overload Protection (kW & kV Ar)
- Low Oil Pressure Protection
- High Coolant Temperature Protection
- Low Fuel Level Protection
- Alternator Battery Charging Failure
- Overspeed Protections
- Oil Pressure and Engine Temperature Readout

Fuel Level Analog Instrument

Emergency Stop Button

Remote Start/Auto Panel Connector

On/Off Switch

AVR Voltage Regulator

The AVR is essential to make the generator work at its best, in fact it all needs an electronic control system, an AVR in fact, which ensures the proper functioning of the machine and the electrical network behind it.

The purpose of the AVR, in a current generator, is to keep the output stable. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed phase shift current counteracts the inductor magnetic field, causing a voltage drop at the alternator terminals; to compensate for this phenomenon, the AVR intervenes automatically by increasing the excitation current, until it returns to the nominal value. If the load is capacitive, the current acts as a magnetizer for the inductor causing an increase in voltage exit, and the AVR intervenes by reducing the excitation current.

TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Urban-Rent G15000KS-M5 15,0KVA

Phase Type: SinglePhase / ThreePhase

SinglePhase Continuous Power: 4.5KVA / 3.6KW

SinglePhase Maximum Power: 5.0KVA / 4.0KW

ThreePhase Continuous Power: 13.5KVA / 10.8KW

ThreePhase Maximum Power: 15.0KVA / 11.9KW

Motor: Kohler KDW1003

Emissions Standard: Stage V

Starting: Electric

Power Supply: Diesel

Receptacle Panel: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V

Voltage: 230 / 400 V

Frequency: 50 Hz

Motor RPM: 3000 rpm  
Tank Capacity: 50 l  
Autonomy @ 75%: 14 h fixed revolutions  
Voltage regulator: AVR  
Sound pressure @7m: 67 dBa  
Length (mm): 1475  
Width (mm): 710  
Height (mm): 1060  
Dry weight (Kg): 417

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

**Product features:**

Phase: Single phase / Three phase  
Maximum power single phase (KW): 4  
Continuous power single phase (KW): 3.6  
Maximum power single phase (KVA): 5  
Continuous power single phase (KVA): 4.2  
Maximum power three phase (KW): 11.9  
Continuous power three phase (KW):  
Maximum power three phase (KVA): 15,0  
Continuous power three phase (KVA):  
Fuel: Diesel  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Sockets configuration: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V  
Engine: Kohler KDW1003  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric  
Cooling: Water  
Poles: 2  
Fuel tank capacity (L): 50  
Running time (h): 14  
Acoustic pressure: 67 dB(A) at 7 m  
Length (mm): 1475  
Width (mm): 710  
Height (mm): 1060  
Dry weight (Kg): 417

Silenced: Yes

Super silenced: Yes

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Kohler