

GENMAC Infinity-Rent G15KS-M5 GENERATOR 15,4KVA



Product description:

GENMAC Infinity-Rent G15KS-M5 THREE-PHASE GENERATOR 15,4KVA

The generator GENMAC Infinity-Rent G15KS-M5 three-phase is equipped with a Kohler diesel-powered engine capable of delivering a power of 15,4KVA with AVR voltage regulator.

The generator is equipped with an oversized Kohler engine capable of delivering a continuous power of 14.4KVA and a maximum power of 15,4KVA. Thanks to the 50l tank the Genmac Infinity generator has an autonomy of up to 14 hours of work.

The Genmac generator silenced has been realized with a high performance frame to minimize the sound pressure. The frame is made with steel plates made according to UNI S235JR standards, complete with rubber anti-vibration supports. In order to improve the handling before use, at the base of the generator there are bilateral steel pockets for forklift trucks, which allows lifting from all sides, and on the top of the generator there is a hook for central lifting.

The 15,4KVA generator is complete with 4 doors that allow easy access for ordinary or extraordinary maintenance. In order to make this Genmac generator as quiet as possible, 100% recyclable, fireproof, self-extinguishing, fireproof, washable, class 1 reaction to fire, mechanically fixed to the frame.

The Genmac Infinity-Rent silenced generator specific for mobile and rental applications. Easy to use and move. It mounts the latest generation engine with low emissions, for energy that respects the environment.

Control Panel

The control panel is composed as follows:

No. 1 CEE 32A 400V

No. 1 CEE 16A 400V



No. 2 CEE 16A 230V
 No. 1 Schuko 16A 230V
 Thermal switch
 Magnetothermal switch
 DSE4510 control panel

- Generator power reading (kW, kV Ar, kV A & pf)
- Overload Protection (kW & kV Ar)
- Low Oil Pressure Protection
- High Coolant Temperature Protection
- Low Fuel Level Protection
- Alternator Battery Charging Failure
- Overspeed Protections
- Oil Pressure and Engine Temperature Readout

Fuel Level Analog Instrument
 Emergency Stop Button
 Remote Start/Auto Panel Connector
 On/Off Switch

AVR Voltage Regulator

The AVR is essential to make the generator work at its best, in fact it all needs an electronic control system, an AVR in fact, which ensures the proper functioning of the machine and the electrical network behind it.

The purpose of the AVR, in a current generator, is to keep the output stable. And if its operation is very simple when resistive loads are fed, more complex is the matter in case of mainly inductive loads: the delayed phase shift current counteracts the inductor magnetic field, causing a voltage drop at the alternator terminals; to compensate for this phenomenon, the AVR intervenes automatically by increasing the excitation current, until the returns to the nominal value. If the load is capacitive, the current acts as a magnetizer for the inductor causing an increase in voltage exit, and the AVR intervenes by reducing the excitation current.

TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Infinity-Rent G15KS-M5 15,4KVA

Phase Type: SinglePhase / ThreePhase
 SinglePhase Continuous Power: 4.8KVA / 3.8KW
 SinglePhase Maximum Power: 5.1KVA / 4.1KW
 ThreePhase Continuous Power: 14.4KVA / 11.5KW
 ThreePhase Maximum Power: 15.4KVA / 12.3KW
 Motor: Kohler KDW1603
 Emissions Standard: Stage V
 Starting: Electric
 Power Supply: Diesel
 Receptacle Panel: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V



Voltage: 230 / 400 V
Frequency: 50 Hz
Motor RPM: 1500 rpm
Tank Capacity: 50 l
Autonomy @ 75%: 14 h fixed revolutions
Voltage regulator: AVR
Sound pressure @7m: 67 dBa
Length (mm): 1802
Width (mm): 752
Height (mm): 1130
Dry weight (Kg): 558

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 4.1
Continuous power single phase (KW): 3.8
Maximum power single phase (KVA): 5.1
Continuous power single phase (KVA): 4.8
Maximum power three phase (KW): 12.3
Continuous power three phase (KW): 11.5
Maximum power three phase (KVA): 15.4
Continuous power three phase (KVA): 14.4
Fuel: Diesel
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x Schuko 16A 230V - 2 x 16A 230V - 1 x 16A 400V - 1 x 32A 400V
Engine: Kohler KDW1603
Emissions Regulations: Stage 5
Engine rpm (rpm): 1500
Starting system: Electric
Cooling: Water
Poles: 2
Fuel tank capacity (L): 50
Running time (h): 14
Acoustic pressure: 67 dB(A) at 7 m
Length (mm): 1802
Width (mm): 752

Height (mm): 1130
Dry weight (Kg): 558
Silenced: Yes
Super silenced: Yes
ATS Switch device : Optional
Voltage regulator: AVR
Engine manufacturer: Kohler