



# CGM CS18000T THREE-PHASE GENERATOR STAGE V 19,2KVA

Product price:

**6.810,00 € tax excluded**

## Product description:

CGM CS18000T THREE-PHASE GENERATOR STAGE V 19,2KVA

CGM CS18000T three-phase generator of 19,2 KVA with BRIGGS & STRATTON engine powered by STAGE V Gasoline at 3000 rpm, compact and easy to use.

The CGM CS18000T generator consists of an NSM Made in Italy, self-excited brushless alternator with **AVR** voltage regulator. The CGM CS18000T is equipped with electric start with battery that allows a practical and fast use even when cold. The CGM CS18000T has a low fuel consumption, in fact it consumes only 6,5 liters/hour at 75% of the load.

The generator CGM CS18000T is part of the QUIET series because thanks to the hood has low noise emissions and is supersilenced. This generator is 3000 RPM, with BRIGGS & STRATTON engine with electric start with key and battery.

## Technical features of the CGM CS18000T:

Phase Type: Single-Three Phase  
Singlephase Continuous power: 9 KW  
ThreePhase Maximum Power: 15.3 KW  
ThreePhase Continuous Power: 14 KW  
ThreePhase Maximum Power: 19.2 KVA  
Threephase Continuous power: 17.5 KVA  
Fuel: Gasoline  
Voltage: 230 / 400 V  
Frequency: 50 Hz  
Engine: BRIGGS & STRATTON 31HP  
Cooling: Air  
Number of cylinders: 2  
Emissions standard: Stage V

Engine RPM: 3000 rpm  
Starter: Electric  
Alternator: NSM made in Italy  
Voltage regulator system: AVR  
Consumption: 6.5 Lt/h at 75% of the load  
Tank capacity: 60 Lt  
Autonomy: 9.2 h at 75% load  
Length: 1200 mm  
Width: 700 mm  
Height: 900 mm  
Weight: 280 Kg  
Supersilenced

Manual electric panel with:  
n. 1 CEE 16A 3P 230V socket  
n. 1 CEE 32A 5P 400V socket  
General switch  
connector for ATS  
hour counter

Discover the full range of current generator of CGM on our catalog to find the one that best suits your needs.

Pictures and technical data not binding.

**Product features:**

Phase: Single phase / Three phase  
Continuous power single phase (KW): 9  
Maximum power three phase (KW): 15.3  
Continuous power three phase (KW): 14  
Maximum power three phase (KVA): 19.2  
Continuous power three phase (KVA): 17.5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400



---

Sockets configuration: 1 x 230V 63A 3P CEE - 1 x 230V 16A 3P - 1 x 230V SCHUKO  
Engine: BRIGGS & STRATTON 31HP  
Emissions Regulations: Stage 5  
Engine rpm (rpm): 3000  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 896  
Number cylinders: 2  
Cooling: Air  
Alternator: NSM, made in Italy  
Fuel tank capacity (L): 60  
Consumption (L/h): 6.5 @ 75%  
Running time (h): 9.2  
Length (mm): 1200  
Width (mm): 700  
Height (mm): 900  
Dry weight (Kg): 280  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : Optional  
Voltage regulator: AVR  
Engine manufacturer: Briggs&Stratton  
Video: MKDdx7hAnHc

