



GENMAC Whisper-GAS G12000KS-M5 NG GENERATOR 11,0KVA

Product description:

GENMAC Whisper-GAS G12000KS-M5 NG THREE-PHASE GENERATOR 11,0KVA

The generator Genmac Whisper-GAS G12000KS-M5 NG three-phase is equipped with a Kohler engine powered by methane gas capable of delivering a power of 11,0KVA with capacitor voltage regulator (AVR optional).

Genmac silenced professional high quality natural generator with 11,0KVA power produced. Genmac is equipped with an oversized air-cooled Kohler engine.

Genmac professional methane generators are highly reliable machines, built with quality components to be used in the professional field, where reliability is fundamental.

This feature is fundamental to guarantee a high reliability of the generator, reduces its effort and increases its life span by lowering the noise level.

All Kohler engines are built using the best materials, the most innovative techniques and the most advanced methods for quality control.

Each engine is thoroughly tested in order to prove its perfect functioning before delivery.

In case of need, Kohler assistance service is always at your disposal.

The 11,0KVA generator is equipped with a capacitor voltage regulator, on request it can be supplied with the AVR regulator.

AVR Voltage Regulator

All Genmac series models are available with optional AVR voltage regulator. The AVR is a device that allows to keep the output more constant and less dependent on the load. Thanks to this card you have fewer drops or current peaks and this makes it safer to use the various devices connected, improving performance and durability.

The model equipped with AVR board is highly recommended, as it guarantees a significant

improvement in the stability of the output; this feature makes the generators particularly suitable for common use machines with reactive load such as refrigerators, freezers, air conditioners and garden machines. Thanks to the AVR you will enjoy greater stability and therefore an increase in the life of your devices.

TECHNICAL CHARACTERISTICS OF GENERATOR GENMAC Whisper-GAS G12000KS-M5 NG 11,0KVA

Voltage regulator : capacitor (AVR Optional)

Power supply: Natural gas

Starting: Electric

Phase type: Single phase / Three phase

Single phase continuous power: 3.3KVA / 2.6KW

Maximum Single-Phase Power: 3.6KVA / 2.9KW

Maximum Three-Phase Continuous Power: 10.0KVA / 8.0KW

Maximum Three-Phase Power: 11.0KVA / 8.8KW

Motor: Kohler CH730

Emissions Standard: Stage V

Socket panel: 1 x Schuko 16A 230V / 1 x 32A 230V / 1 x 32A 400V

Voltage: 230 / 400 V

Frequency: 50 Hz

3000 rpm

Autonomy @ 75%: 3.3 h fixed revolutions

Acoustic Pressure: 65 dB(A) @ 7 m

Length (mm): 1100

Width (mm): 540

Height (mm): 924

Dry weight (Kg): 257

If you are looking for another product then you can consult other terrestrial generators in our catalog.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2.9

Continuous power single phase (KW): 2.6

Maximum power single phase (KVA): 3.6

Continuous power single phase (KVA): 3.3

Maximum power three phase (KW): 8.8

Continuous power three phase (KW): 8
Maximum power three phase (KVA): 11
Continuous power three phase (KVA): 10
Fuel: Natural Gas
Frequency (Hz): 50
Voltage (V): 230 / 400
Sockets configuration: 1 x 400V 32A CEE - 1 x 230V 32A CEE - 1 x 230V 16A SCHUKO
Engine: Kohler CH730
Emissions Regulations: Stage 5
Engine rpm (rpm): 3000
Starting system: Electric
Cooling: Air
Poles: 2
Natural Gas consumption (m³/h): 3.3
Acoustic pressure: 65 dB(A) at 7 m
Length (mm): 1100
Width (mm): 540
Height (mm): 924
Dry weight (Kg): 257
Silenced: Yes
Super silenced: Yes
ATS Switch device : Optional
Voltage regulator: Compound / AVR (optional)
Engine manufacturer: Kohler