

MOSA GE S-8000 HBT 60Hz



Product price:

1.823,35 € tax excluded

Product description:

MOSA GES-8000 HBT 60Hz 6,4 KW

MOSA GES-8000 HBT 60Hz is a three-phase generating set with a gasoline-powered Honda engine capable of delivering a maximum power of 6.4 KW. The MOSA GES-8000 HBT generating set is equipped with a manual recoil starter. The alternator of the MOSA GES-8000 HBT generating set is synchronous, three-phase, self-excited, self-regulated with class H insulation.

MOSA is compact and convenient to maneuver and transport thanks to its compact size, its weight of 98 kg as well as the practical tubular handles.

The MOSA GES-8000 HBT generator set with 20-liter tank has a fuel consumption of 2.4 liters/hour at 75% load for up to 8 hours autonomy.

Technical specifications MOSA GES-8000 HBT:

Three-phase output Stand-by (LTP): 8 kVA (6.4 kW)

Three-phase output PRP: 7 kVA (5.6 kW)

Single-phase output PRP 4 kW

Frequency: 50 Hz

Cos ϕ : 0.8

ENGINE TECHNICAL DATA

Model: HONDA GX 390

Net stand-by output: 8.2 kWm (11.1 hp)

Net PRP output: 6.4 kWm (8.7 hp)

Cylinders / Displacement: 1 / 389 cm³ (0.39 lt.)

Bore / Stroke: 88 / 64 (mm)

Compression ratio: 8.2 : 1

RPM controller: Mechanical

FUEL CONSUMPTION

110 % (Stand-by power): 3.5 lt./h

100 % PRP: 3.2 lt. /h

75 % PRP: 2.4 lt./h

50 % PRP: 1.6 lt./h

Cooling system: Air

Sump oil capacity: 1.1 lt.

ALTERNATOR CHARACTERISTICS

Continuous power: 7 kVA

Standby power: 7.7 KVA

Single-phase voltage: 120 / 220 V

Frequency: 60 Hz

Voltage regulation accuracy: ± 4 %

Sustained short-circuit current: 3 In

Transient Cdt (100 % load): 15 %

Efficiency at 100 % load: 80.5 % (400V - Cos ϕ 0.8)

Isolation: Class H

Connection - Terminals: Series - N°6

Electromagnetic Compatibility (Radio Interference Suppression): EN55011

Harmonic Distortion - THD: Direct Synchronous - Xd: 270 %

Direct Transient - X'd: 20 %

Direct Subtransient - X "d: 6.5 %

Quad Synchronous. - Xq: 150 %

Transitory - T'd: 33 ms

Subtransitory - T "d: 5.5 ms

Unloaded - T'do: 450ms

Short-circuit ratio Kcc: 0.60

Protection degree: IP 23

Cooling air flow: 0.062/m³/sec

Coupling - Bearings: Direct J609b - N°1

GENERAL SPECIFICATIONS

Tank capacity: 20 lt.

Run time (75% of PRP): 8.5 h

Measured acoustic power LwA (LpA pressure): 96 dB(A) (71 dB(A) @ 7m)

Guaranteed acoustic power LwA (LpA pressure): 96 dB(A) (71 dB(A) @ 7m)

Performance class: G2

Length: 770 mm

Width: 520 mm

Height: 650 mm

Weight: 98 Kg

MOSA GES-8000 HBT portable generator set - Honda gasoline engine recoil start - Three-phase alternator - Three-phase power 7 kVA (5.6 kW)

**Features:**

- Recoil start
- Engine stop for low oil level
- Magnetothermal switch
- Fuel level indicator
- Protective and partially enclosed stretcher
- Silenced
- Portable
- Complies with EC directives for noise and safety
- AVR version on request

If you are looking for another product such as MOSA GES-8000 HBT generator set then you can browse our catalog for more terrestrial generator sets.

Images and technical data are not binding.

.

Product features:

Phase: Single phase / Three phase

Continuous power single phase (KW): 4

Continuous power single phase (KVA): 5

Maximum power three phase (KW): 6.4

Continuous power three phase (KW): 5.6

Maximum power three phase (KVA): 8

Continuous power three phase (KVA): 7

Fuel: Gasoline

Frequency (Hz): 60

Voltage (V): 120 / 220

Engine: Honda GX390, 4 stroke, OHV

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 389

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous self-excited, self-regulated

Bore x stroke (mm): 88 x 64





Fuel tank capacity (L): 20
Consumption (L/h): 2.4 at 75% of the load
Running time (h): 8.3 at 75% of the load
Acoustic pressure: 71 dB(A) at 7 m
Length (mm): 770
Width (mm): 520
Height (mm): 650
Dry weight (Kg): 98
Silenced: Yes
Super silenced: No
ATS Switch device : No
Voltage regulator: Compound / AVR (optional)

