



# PRAMAC ES3000 SINGLE PHASE AVR

Product price:

**1.063,50 € tax excluded**

## Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated. Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

## Product features:

Phase: Single phase  
Maximum power single phase (KW): 2.6  
Continuous power single phase (KW): 2.2  
Maximum power single phase (KVA): 2.9  
Continuous power single phase (KVA): 2.5  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230



---

Sockets configuration: 2 x 230V 16A IP54 SCHUKO  
Engine: Honda GX160, naturally aspirated  
Engine rpm (rpm): 3000  
Speed governor: Mechanical  
Ignition: Recoil  
Starting system: Pull starter  
Engine capacity (cm<sup>3</sup>): 163  
Oil capacity (L): 0.6  
Cooling: Air  
Alternator: With brushes  
Poles: 2  
Fuel tank capacity (L): 11  
Consumption (L/h): 0.9 at 75% of the load / 1.2 at 100% of the load  
Running time (h): 12.5 at 75% of the load / at 100% of the load  
Acoustic power: 96 dB(A)  
Acoustic pressure: 68 dB(A) at 7 m  
Length (mm): 623  
Width (mm): 409  
Height (mm): 500  
Dry weight (Kg): 43  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Honda