



PRAMAC ES5000 THREE PHASE AVR

Product price:

1.999,50 € tax excluded

Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated. Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

Product features:

Phase: Single phase / Three phase
Maximum power single phase (KW): 3.04
Continuous power single phase (KW): 2.8
Maximum power single phase (KVA): 3.8
Continuous power single phase (KVA): 3.5
Maximum power three phase (KW): 5
Continuous power three phase (KW): 4.3
Maximum power three phase (KVA): 6.3
Continuous power three phase (KVA): 5.4



Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE IP44 - 1 x 230V 16A SCHUKO IP54 - 1 x 230V 16A 2P+T CEE IP44

Engine: Honda GX270 Recoil, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm³): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 11

Consumption (L/h): 1.6 at 75% of the load / 2.2 at 100% of the load

Running time (h): 6.6 at 75% of the load / 5 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 729

Width (mm): 500

Height (mm): 536

Dry weight (Kg): 75

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: Honda