



# PRAMAC ES8000 SINGLE PHASE AVR

Product price:

**2.090,25 € tax excluded**

## Product description:

Model with gasoline fuel supply, characterized by a strong structure with tubular frame and adequate protections in sheet steel with oversized tank incorporated. Designed to satisfy long lasting professional and intensive applications.

HONDA GX series petrol engines

- ? Air cooling
- ? Oil Guard protection
- ? Tear-off starter
- ? Synchronous alternators available with AVR
- ? Sturdy structure with tubular supporting frame
- ? Sockets on headphones with thermal protection.
- ? Oversized tanks (11 litres)
- ? Side protection strips

The image is purely indicative.

## Product features:

Phase: Single phase  
Maximum power single phase (KW): 6.4  
Continuous power single phase (KW): 5.5  
Maximum power single phase (KVA): 7.2  
Continuous power single phase (KVA): 6  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230



---

Sockets configuration: 1 x 230V 16A SCHUKO IP54 - 1 x 230V 32A 2P+T CEE IP44  
Engine: Honda GX390 Recoil, naturally aspirated  
Engine rpm (rpm): 3000  
Speed governor: Mechanical  
Ignition: Recoil  
Starting system: Pull starter  
Engine capacity (cm<sup>3</sup>): 389  
Oil capacity (L): 1.1  
Cooling: Air  
Alternator: With brushes  
Poles: 2  
Fuel tank capacity (L): 11  
Consumption (L/h): 2.1 at 75% of the load / 2.9 at 100% of the load  
Running time (h): 5.1 at 75% of the load / 3.8 at 100% of the load  
Acoustic power: 97 dB(A)  
Acoustic pressure: 69 dB(A) at 7 m  
Length (mm): 729  
Width (mm): 500  
Height (mm): 536  
Dry weight (Kg): 73  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: Honda