



# PRAMAC PX3250



## Product description:

## Product features:

Phase: Single phase

Maximum power single phase (KW): 2.6

Continuous power single phase (KW): 2.2

Maximum power single phase (KVA): 2.8

Continuous power single phase (KVA): 2.3

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V 16A IP54 SCHUKO

Engine: Honda GP160, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm<sup>3</sup>): 163

Oil capacity (L): 0.58

Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 3.1

Consumption (L/h): 0.88 at 75% of the load / 1.16 at 100% of the load

Running time (h): 3.52 at 75% of the load / 2.65 at 100% of the load

Acoustic power: 95 dB(A)

Acoustic pressure: 71 dB(A) at 7 m

Length (mm): 625



---

Width (mm): 455  
Height (mm): 455  
Dry weight (Kg): 38  
Silenced: No  
Super silenced: No  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: Capacitor  
Engine manufacturer: Honda