



# PRAMAC PX8000 GENERATOR SINGLE PHASE / THREE PHASE 6 KVA AVR

Product price:

**939,00 € tax excluded**

## Product description:

PRAMAC PX8000 GENERATOR SINGLE PHASE / THREE PHASE 6 KVA AVR

PRAMAC PX8000 singlephase / threephase generator with PRAMAC AP190F engine powered by gasoline, capable of delivering a power of 6 KVA complete with AVR voltage regulator.

The PRAMAC PX8000 generator is equipped with electric start with battery, but it is also equipped with a rope recoil starter for manual start. The alternator of the PRAMAC PX8000 is with AVR voltage regulator.

The gasoline engine PRAMAC AP190F makes the generator very reliable as it has been built and designed using high quality materials.

Due to its very low weight and compact size, it is convenient to carry where you need it most. This generator is suitable for outdoor use in small construction sites or for small outdoor work for hobby use.

This gasoline generator represents one of the latest innovations of Pramac to ensure a high level of quality and performance at an attractive price. The PRAMAC PX8000 is compact, efficient and easy to use. The genset is perfect for all your semi-professional applications.

## TECHNICAL FEATURES PRAMAC PX8000:

Phase type: Single-phase/Three-phase  
Single-phase continuous power use: 1.6 KVA / 1.2 KW  
Maximum single-phase power: 2 KVA / 1.5 KW  
Three-phase continuous use power: 5 KVA / 4 KW  
Maximum three-phase power: 6 KVA / 4.8 KW



Motor: Pramac SR190F  
Motor speed: 3000 rpm  
Emissions regulations: Not emitted  
Starter: Electric / Manual  
Fuel: Petrol  
Voltage: 230 / 400 V  
Frequency: 50 Hz  
Socket panel: 1 x SCHUKO 230V 16A / 1 x 2P+E CEE 230V 16A / 1 x 3P+N+E CEE 400V 16A  
Tank capacity: 27 l  
Acoustic power (LWA) dBA 97  
Acoustic pressure: 69 dB(A) @ 7 m  
Length: 727 mm  
Width: 515 mm  
Height: 670 mm  
Dry weight: 97 Kg  
Autonomy at 75% load h 13.11  
Autonomy at 100% load h 9.82

#### CONTROL PANEL

Controls:

- Start key: OFF - ON - START

Instrumentation:

- Voltmeter
- Ammeter
- Frequency meter
- Fuel level indicator

Protections:

- Thermal Protection
- Oil Guard (low oil level)

Sockets

- N.1 SCHUKO 230V 16A IP54
- N.1 2P+T CEE 230V 16A IP44
- N.1 3P+N+T CEE 400V 16A IP44

Are you looking for a generator with different technical features? [HERE](#) you can find the area dedicated to PRAMAC generator or other specialized brands.





Images and technical data are not binding.

### Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 1.6

Continuous power single phase (KW): 1.2

Maximum power single phase (KVA): 2

Continuous power single phase (KVA): 1.5

Maximum power three phase (KW): 4.8

Continuous power three phase (KW): 4

Maximum power three phase (KVA): 6

Continuous power three phase (KVA): 5

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: PRAMAC SR190F, naturally aspirated

Emissions Regulations: Stationary Use

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 420

Oil capacity (L): 1.1

Cooling: Air

Poles: 2

Fuel tank capacity (L): 27

Consumption (L/h): 2.75

Running time (h): 9.8

Acoustic pressure: 69 dB(A) at 7 m

Length (mm): 727

Width (mm): 515

Height (mm): 670

Dry weight (Kg): 97

Silenced: Yes

Super silenced: Yes

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: PRAMAC

