

# PRAMAC S12000 THREE PHASE DPP AVR



**Product price:**

**4.921,50 € tax excluded**

## **Product description:**

PRAMAC S12000 THREE PHASE DPP AVR.

Introducing the PRAMAC S12000, a state-of-the-art three-phase generator with DPP AVR technology. Designed to deliver consistent and reliable power, this model ensures optimal voltage stability across all operations. The PRAMAC S12000 epitomizes high-end performance coupled with precision engineering, making it an indispensable asset for diverse power needs.

Motor Honda Serie GX.

The image is purely indicative

## **Product features:**

Phase: Single phase / Three phase

Maximum power single phase (KW): 4.48

Continuous power single phase (KW): 4

Maximum power single phase (KVA): 5.6

Continuous power single phase (KVA): 5

Maximum power three phase (KW): 11.1

Continuous power three phase (KW): 9.5

Maximum power three phase (KVA): 13.9

Continuous power three phase (KVA): 11.8

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 2 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO



Engine: Honda GX160, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm<sup>3</sup>): 688

Oil capacity (L): 1.9

Cooling: Air

Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 4.23 at 75% of the load / 5.63 at 100% of the load

Running time (h): 5.67 at 75% of the load / 4.26 at 100% of the load

Acoustic power: 96 dB(A)

Acoustic pressure: 72 dB(A) at 7 m

Length (mm): 960

Width (mm): 641

Height (mm): 667

Dry weight (Kg): 165

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda