

PRAMAC S5000 SINGLE PHASE AVR



Product price:

2.523,00 € tax excluded

Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

Product features:

Phase: Single phase

Maximum power single phase (KW): 4.8

Continuous power single phase (KW): 3.9

Maximum power single phase (KVA): 5.3

Continuous power single phase (KVA): 4.2

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 16A 2P+T CEE - 1 x 230V 32A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Honda GX270 Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric

Engine capacity (cm³): 270

Oil capacity (L): 1.1

Cooling: Air

Alternator: With brushes

Poles: 2

Fuel tank capacity (L): 26.5

Consumption (L/h): 1.66 at 75% of the load / 2.21 at 100% of the load

Running time (h): 15.96 at 75% of the load / 11.94 at 100% of the load

Acoustic power: 97 dB(A)

Acoustic pressure: 73 dB(A) at 7 m

Length (mm): 840

Width (mm): 615

Height (mm): 753

Dry weight (Kg): 89

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: AVR

Engine manufacturer: Honda