



# PRAMAC S6000



Product price:

**3.840,00 € tax excluded**

## Product description:

Motore Honda Serie GX. Raffreddamento ad aria. Batteria fornita di serie. Protezione Oil Guard. Tubazioni telaio maggiorate. Serbatoio maggiorato. Bandelle laterali di protezione

L'immagine è puramente indicativa

## Product features:

Phase: Single phase / Three phase

Maximum power single phase (KW): 2.56

Continuous power single phase (KW): 2.4

Maximum power single phase (KVA): 3.2

Continuous power single phase (KVA): 3

Maximum power three phase (KW): 5.5

Continuous power three phase (KW): 4.5

Maximum power three phase (KVA): 6.9

Continuous power three phase (KVA): 5.6

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: 1 x 400V 16A 3P+N+T CEE - 2 x 230V 16A 2P+T CEE - 1 x 230V 16A SCHUKO

Engine: Yanmar L100N Electric, naturally aspirated

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Electric



Engine capacity (cm<sup>3</sup>): 435

Oil capacity (L): 1.6

Cooling: Air

Alternator: Brushless

Poles: 2

Fuel tank capacity (L): 24

Consumption (L/h): 1.45 at 75% of the load / 1.94 at 100% of the load

Running time (h): 16.55 at 75% of the load / 12.37 at 100% of the load

Length (mm): 840

Width (mm): 641

Height (mm): 696

Dry weight (Kg): 124

Silenced: No

Super silenced: No

Product type: Generator

ATS Switch device : Optional

Voltage regulator: Compound

Engine manufacturer: Yanmar