



# POWERMATE WX 6250 SINGLE-PHASE / THREE- PHASE GENERATOR 7.7 KVA AVR

**Product price:**

**840,00 € tax excluded**

## **Product description:**

POWERMATE WX 6250 SINGLE-PHASE / THREE-PHASE GENERATOR 7.7 KVA AVR

POWERMATE WX6250 is a singlephase / threephase generator equipped with a 4-stroke gasoline engine with electric start, capable of delivering a maximum power of 7.7 KVA complete with AVR voltage regulator.

The threephase POWERMATE WX6250 Generator, is equipped with sturdy handles and wheels that allow easy portability; like the entire POWERMATE WX6250 range, it is a generator set that meets a high standard of quality and guarantees a high level of reliability.

The strengths of the POWERMATE WX6250 are: the high quality of components, light weight, compactness, portability and ease of use and also modern design.

The POWERMATE WX6250 has been specially developed for camping, caravans, homes, and hobby applications, etc., so it reflects distinctive features and convenience that allow it to be reliable and convenient in application areas.

## The Advantages of AVR

The automatic voltage regulator, or AVR, enables the POWERMATE WX6250 to deliver stable power and thus be able to connect equipment with sensitive electronics such as computers, household appliances, smartphones and tablets: the genset is therefore ideal for use in the home, camping, hobbies and leisure time, as well as for construction sites and craftsmen.

The AVR voltage regulator and the other quality standard of the alternator with copper windings will provide you with safe and stabilized power.



---

## Technical Features of the POWERMATE WX 6250

Phase Type: SinglePhase / ThreePhase  
Continuous SinglePhase output: 2.25KVA / 1.8 KW  
Maximum SinglePhase output: 2.5KVA / 2 KW  
Continuous ThreePhase output: 6.9KVA / 5.5 KW  
Maximum ThreePhase output: 7.7KVA / 6.1 KW  
VAC Voltage: 230 / 400 V  
Frequency (Hz): 50  
Voltage Regulator: AVR  
Starting Frame: Electric / Manual  
Engine: OHV 4-stroke  
Emission Standard: Stage V  
RPM: 3000  
Power supply: Gasoline  
Fuel tank capacity: 26 l  
Consumption @ 75 % load: 2.17 l/h  
Autonomy @ 75 % load: 12 h  
Sound pressure: 69 dB(A) @ 7m  
Length: 800 mm  
Width: 698 mm  
Height: 620 mm  
Net weight: 90 Kg

Are you looking for a generator with different technical characteristics? Here you can find the area dedicated to POWERMATE generators or other specialized brands

Pictures and data are not binding and may be subject to revisions.

### Product features:

Phase: Single phase / Three phase  
Maximum power single phase (KW): 2  
Continuous power single phase (KW): 1.8  
Maximum power single phase (KVA): 2.5  
Continuous power single phase (KVA): 2.25  
Maximum power three phase (KW): 6.1  
Continuous power three phase (KW): 5.5  
Maximum power three phase (KVA): 7.7  
Continuous power three phase (KVA): 6.9  
Fuel: Gasoline  
Frequency (Hz): 50  
Voltage (V): 230 / 400



Sockets configuration: 1 x 400V - 2 x 230V

Engine: OHV 4-stroke

Emissions Regulations: Stage 5

Engine rpm (rpm): 3000

Speed governor: Mechanical

Starting system: Manual / Electric

Cooling: Air

Fuel tank capacity (L): 26

Consumption (L/h): 2.16

Running time (h): 12

Acoustic pressure: 68 dB(A) at 7 m

Length (mm): 800

Width (mm): 698

Height (mm): 620

Dry weight (Kg): 90

Inverter: No

AVR: Yes

Compound: No

Silenced: No

Super silenced: No

ATS Switch device : No

Voltage regulator: AVR

