



# MOSA GE S-5000 HBM, AVR

**Product price:**

**1.627,62 € tax excluded**

## **Product description:**

MOSA GE S-5000 HBM 4,4 KW AVR

MOSA GE S-5000 HBM AVR is a single-phase generating set with a Honda gasoline engine capable of delivering a power of 4.4 KW. The MOSA GE S-5000 HBM generator set is equipped with a manual recoil starter. The alternator of the MOSA GE S-5000 HBM generator set is synchronous, single-phase, self-excited, self-regulated, brushless with class H insulation and with AVR voltage regulator.

MOSA is compact and convenient to maneuver and transport due to its compact size, 76 kg weight as well as convenient tubular handles. Generator set with partial cowling to reduce noise emissions.

The MOSA GE S-5000 HBM generator set with 20-liter tank has a fuel consumption of 1.6 liters/hour at 75% load for up to 12 hours autonomy.

## **Sockets:**

1x230V 32A 2P+E CEE

1x230V 16A 2P+E CEE

1x230V 16A 2P+E Schuko

## **Technical Specifications MOSA GE S-5000 HBM:**

Single-phase Stand-by Output (LTP): 4.9 kVA (4.4 kW) / 230V / 21.3A

Single-phase Stand-by Output (LTP): 4.9 kVA (4.4 kW) / 115V / 42.6A

Single-phase PRP output: 4 kVA (3.6 kW) / 230V / 17.4A

Single-phase PRP output: 4 kVA (3.6 kW) / 115V / 34.8A

Frequency: 50 Hz

Cos?: 0.9

MOTOR TECHNICAL DATA



Model: HONDA GX 270

Net stand-by output: 5.7 kWm (7.7 hp)

Net PRP output: 4.6 kWm (6.2 hp )

Cylinders / Displacement: 1 / 270 cm<sup>3</sup> (0.27 lt.

Bore / Stroke: 77 / 58 (mm)

Compression ratio: 8.5 : 1

RPM controller: Electronic

#### FUEL CONSUMPTION

110 % (Stand-by power): 2.4 lt./h

100 % PRP: 2.1 lt. /h

75 % PRP: 1.6 lt./h

50 % PRP: 1.1 lt./h

Cooling system: Air

Capacity oil in sump 1.1 lt.

#### ALTERNATOR

Continuous power: 4.5 kVA

Standby power: 5 kVA

Single-phase voltage: 230 Vac

Frequency: 50 Hz

Cos?: 1

Voltage regulation accuracy:  $\pm 1$  %

Sustained short-circuit current: 3 In

Transient Cdt (100 % load): Efficiency at 100 % load: 76 % (230V - Cos ? 1)

80.5 % (400V - Cos ? 1)

Isolation: Class H

Connection - Terminals: Series - No. 2

Electromagnetic compatibility (Radio Interference Suppression): EN55011

Harmonic distortion - THD: Protection degree: IP 23

Cooling air flow: 0.062/ m<sup>3</sup>/sec

Coupling - Bearings: Direct J609b - N°1

#### GENERAL SPECIFICATIONS

Tank capacity: 20 lt.

Run time (75% of PRP): 12.5 h

Measured acoustic power LwA (LpA pressure): 95 dB(A) (70 dB(A) @ 7m)

Guaranteed acoustic power LwA (LpA pressure): 96 dB(A) (71 dB(A) @ 7m)

Performance class: G2

Length: 770 mm

Width: 520 mm

Height: 650 mm

Weight: 76 Kg

#### Features:

- Recoil start

- Engine stop for low oil level
- Magnetothermal switch
- Fuel level indicator
- Protective and partially hooded stretcher
- Silenced
- Portable
- Complies with CE directives for noise and safety
- AVR voltage regulator

If you are looking for another product such as MOSA GE S-5000 HBM AVR generator set then you can browse our catalog for more terrestrial generator sets.

Images and technical data are not binding.

#### **Product features:**

Phase: Single phase

Maximum power single phase (KW): 4.4

Continuous power single phase (KW): 3.6

Maximum power single phase (KVA): 4.9

Continuous power single phase (KVA): 4

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 1 x 230V 32A 2P+T CEE - 1 x 230V 16A 2P+T CEE - 1 x 230V 16A 2P+T SCHUKO

Engine: Honda GX270, 4 stroke, OHV

Emissions Regulations: Stationary Use

Engine rpm (rpm): 3000

Speed governor: Mechanical

Ignition: Recoil

Starting system: Pull starter

Engine capacity (cm<sup>3</sup>): 270

Number cylinders: 1

Oil capacity (L): 1.1

Cooling: Air

Alternator: Synchronous self-excited, self-regulated

Bore x stroke (mm): 77 x 58