



## SINCRO ET2 MBR Three Phase Synchronous AC Alternator 5.5 kVA AVR

### Product description:

Three phase brushes alternator - AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 22.14 / cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE

The image is purely indicative.

### Product features:

Phase: Three phase

Frequency (Hz): 50

Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Poles: 2

Three-phase power (KW): 4.4

Three-phase power (KVA): 5.5

Efficiency (%): 75

Protection degree: IP23

Dry weight (Kg): 25.3

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: AVR

