



## SINCRO FT2 MGR Three Phase Synchronous AC Alternator 18 kVA D-AVR

### Product description:

Three phase brushes alternator - DIGITAL AVR.

- Self-regulated
- IP23
- Standard voltage 230/400 V - 50 Hz
- Short circuit current greater than 3 In
- Standard coupling IM B35 cone 25.4 / cone 35
- Couplings IM B34, IM B35, SAE
- DIGITAL AVR

Not binding images and technical data.

### Product features:

Phase: Three phase  
Frequency (Hz): 50  
Voltage (V): 230 / 400  
Engine rpm (rpm): 3000  
Poles: 2  
Three-phase power (KW): 14.4  
Three-phase power (KVA): 18  
Efficiency (%): 85.4  
Protection degree: IP23  
Dry weight (Kg): 67  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: Digital AVR

