


The **NOMAD POWER PRO 24 XL** is a lithium-based power pack that combines 3 functions :

- **Booster for 24 V vehicles (trucks, plants).**
- **Autonomous power supply for all kinds of electrical appliances.**
- **Emergency lamp.**

LITHIUM BATTERY BOOSTER

Its **lithium** battery (NMC) gives it an exceptional power-to-size ratio (starting current : 1400 A). It starts vehicles equipped with a discharged 24 V battery (liquid, gel, AGM, Start&Stop) in a few seconds ( do not start Lithium LiFePO₄ batteries with this booster, battery voltages not compatible)..

START 	
24 V PETROL & DIESEL	

SAFETY START

All safety features are integrated into the product to protect both the battery and the vehicle's electronic equipment:

- Anti-spark technology,
- Short circuit protection,
- Reverse polarity protection.
- Protection against excessive starting currents,
- Protection against booster temperature increases.

MOBILE ENERGY SOURCE

Its very powerful storage capacity (8 Ah) brings comfort and tranquility to the daily need to stay connected (phone, tablet, computer).

Equipped with:

- **2 USB 5 V - 2.1 A** ports for charging smartphone, tablet, GPS, etc.
- **1 output port 12 V - 3.5 A**, ideal for powering a 12 V electrical appliance (cool box, fan, etc.)

HIGH BRIGHTNESS ASSIST LAMP

Auxiliary light (28 leds) with 3 lighting modes: normal, strobe, SOS.

LCD DISPLAY

The NOMAD POWER PRO 24 XL is equipped with an LCD display that gives information on:

- the % of charge of the internal battery.
- the different input and output ports used.



Colour LCD display



Supplied with accessories:



Charger 230 Vac / 18 Vdc













Strap



Cigarette lighter charger



3 in 1 cable

STARTING				EQUIPMENT				INPUT / OUTPUT				POWER BANK	LED	DIMENSIONS					
Lithium		I		SMART CABLE 			CABLES 			INPUT 	OUTPUT 								
Capacity per cell	Full charge	Start	Cranking CC				Peak Battery	USB-C	MICRO USB Type B		Lightning	IN	5V - 2.1A					12V	15V
8 Ah 236.8 Wh	10 h	1400 A	2400 A	3000 A	—	✓	✓	✓	✓	✓	18V - 2A	2	5V - 2.1A	3.5A	—	✓	3 modes : Light SOS SPOT	27.8 x 11 x 27.4	5.6