

POWERSMART G4000

GENMAC®



MODELLO/MODEL	G4000
Motore/Engine	R270
Tipo/Type	4 Tempi, raffreddato ad aria, monocilindrico 4-Stroke, Air-cooled, single cylinder
Carburante/Fuel	Benzina/Gasoline
Cilindrata/Displacement	270 ml
GENERATORE/GENERATOR	
Frequenza/Frequenc	50 Hz
Tensione Nominale/Rated voltage	230 V
Potenza Nominale/Rated power	3,5 kW
Potenza Massima/Max Power	4 kW
Capacità Serbatoio/Fuel tank capacity	25 litri/litres
Rumorosità/Noise Level	72 dBA@7m
Dimensioni/Dimensions	684x562x557 mm
Peso/Weight	68 kg.
Configurazione	
Livello Carburante/Fuel meter	*
Voltmetro/Volt meter	*
Contatore/Houmeter	-
Frequenzimetro/Frequencymeter	-
Interr. Magnetotermico/Circuit Breaker	*
AVR	*
Allarme Olio/Oil Alarm System	*
Avviamento / Starting	A strappo / Recoil
Prese/Sockets	2 x Presa Schuko 230V - 16A / 2x Schuko socket 230V - 16A
Carica Batteria/DC Sockets	*
Interruttore On-Off	*
kit Carrello	Optional