

type:

gasoline generator

V / Hz Voltage:

230/50

Maximum KW:

4.2

Nominal power:

4

cylinder diameter:

88 x 64

Voltage regulator:

AVR

Engine type:

Monocilindirco 4 times

Engine Model:

CP188F

HP / rpm motor power:

13/3600

Fuel tank capacity / oil (l):

25 / 1.1

starter:

transistor

Manual start:

No

Electric start:

Yes

cc engine capacity:

389

Autonomy with full tanks (h):

10.8

Phase:

1

Noise dBA (4m):

97

Net weight Kg:

78

12V output:

Yes

voltmeter:

Yes

Protection:

Yes

Safety device for lack oil:

Yes