

GREEN POWER GP50S-P-N SUPER SOUNDPROOF

Product price:

10.939,00 € tax excluded

Product description:

Ì

The GREEN POWER 1500 rpm generators are designed for versatile use, from construction sites to industry, from agriculture to civil protection.

Robust welded steel frames with built-in tank of variable capacity produced by Green Power, engines and alternators supplied by the most important manufacturers in the sector and cutting-edge control units are the elements to ensure generators of excellent quality.

The hoods are made of steel, which allows them to be used in tropical environments. The Green Power covers guarantee maximum accessibility for maintenance and cleaning operations.

Green Power's strong point is the design and implementation within the company, a feature that helps to reduce the time to market of the product and allows any customization.

There is a choice of versions:

-Super-silenced group with AVR-Leroy alternator (automatic control unit)

-Super-silenced group with AVR-Mecc alte alternator (automatic control unit)

-Super-silenced group with AVR-Stamford alternator (automatic control unit)

The image is purely indicative.

Product features:

Phase: Three phase Maximum power three phase (KW): 40 Continuous power three phase (KW): 36 Maximum power three phase (KVA): 50

PrestaShop

R



Continuous power three phase (KVA): 45 Fuel: Diesel Frequency (Hz): 50 Voltage (V): 230 / 400 Engine: PERKINS 1103A-33TG1, aspirazione sovralimentata **Emissions Regulations: NON EMISSIONATO** Engine rpm (rpm): 1500 Speed governor: Mechanical Starting system: Elettrico Engine capacity (cm³): 3300 Number cylinders: 3 Cylinders' position: In line Cooling: Water Alternator: MECC ALTE ECP32-1M/4 Poles: 4 Protection degree: IP23 Fuel tank capacity (L): 100 Consumption (L/h): 8.2 al 75% del carico Running time (h): 8.5 at 75% of the load Acoustic pressure: 60 dB(A) Length (mm): 2100 Width (mm): 870 Height (mm): 1165 Dry weight (Kg): 1020 Silenced: Yes Super silenced: Yes ATS Switch device : Optional Voltage regulator: AVR