

# LINZ E1C13M D/2 Single-phase alternator 115/230V 15 kVA 50 Hz Brushless



## Product description:

The E1C13M series consists of single-phase, brushless, 2-pole alternators with auxiliary winding (charged on the condenser) that ensures voltage regulation.

## CHARACTERISTICS

- Compact and easy to assemble
- Possibility of feeding any type of load
- Wide range of accessories
- High efficiency
- Gamma: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: CONDENSER
- Application: FLOW-UP
- Images and technical data are not binding.

## Product features:

Phase: Single phase

Maximum power single phase (KW): 15

Maximum power single phase (KVA): 15

Frequency (Hz): 50 / 60

Voltage (V): 115 / 230

Engine rpm (rpm): 3000

Alternator: Synchronous, brushless

Poles: 2

---

Single-phase power (KVA): 15  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 495  
Width (mm): 270  
Height (mm): 375  
Brushes: No  
Type of alternator: Constant Speed  
Voltage regulator: Capacitor  
Weight (Kg): 77.7