



LINZ E1E13M E Single-phase alternator 115V/230V 18 kVA 50 Hz AVR



Product description:

The **SPE** and **E1E** series consist of single-phase 2-pole alternators with brushes and AVR electronic regulation.

CHARACTERISTICS

- Compact and easy to assemble
- High voltage accuracy
- Wide range of accessories
- AVR with built-in protections
- Range: Single-phase alternators
- Poles: 2
- Phases: Single-phase
- Adjustment: AVR
- Application: PORTABLE
product available 50 Hz and 60 Hz

Images and technical data are not binding.

Product features:

Phase: Single phase

Continuous power single phase (KW): 18

Continuous power single phase (KVA): 18

Frequency (Hz): 50 / 60

Voltage (V): 115 / 230

Engine rpm (rpm): 3000





Alternator: Synchronous, brushless
Poles: 2
Single-phase power (KVA): 18
Protection degree: IP21
Motor insulation class: H
Length (mm): 495
Width (mm): 270
Height (mm): 379
Brushes: Yes
Type of alternator: Constant Speed
Voltage regulator: AVR
Weight (Kg): 89

