



# LINZ E1C13S B/4 Single-phase alternator 115/230V 7 kVA 50 Hz Brushless

## Product description:

**LINZ E1C13/4** series are single-phase 4 poles brushless alternators with an auxiliary winding loaded on a capacitor regulating the voltage.

This series has been designed for application in light towers with metal halide, halogen lamps or LED.

## CHARACTERISTICS

- Innovative rotating diode system
- Low harmonic content
- High efficiency
  
- Type: Single-phase alternators
- Poles: 4
- Phases: Single-phase
- Regulation: CAPACITOR
- Application: PORTABLE, LIGHTING TOWERS  
product available in 50 Hz and 60 Hz versions

## Product features:

Phase: Single phase

Continuous power single phase (KW): 7

Continuous power single phase (KVA): 7

Frequency (Hz): 50 / 60

Voltage (V): 115 / 230

Engine rpm (rpm): 1500

Alternator: Synchronous, brushless



Poles: 4

Single-phase power (KVA): 7

Protection degree: IP21

Motor insulation class: H

Length (mm): 405

Width (mm): 270

Height (mm): 379

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: Capacitor

Weight (Kg): 50.5