



## LINZ E1C13S D/4 Singlephase alternator 110V/230V 11 kVA 60 Hz Brushless

## **Product description:**

**LINZ E1C13/4** series are single-phase 4 poles brushless alternators with an auxiliary winding loaded on a capacitor regulating the voltage.

This series has been designed for application in light towers with metal halide, halogen lamps or LED.

## **CHARACTERISTICS**

- Innovative rotating diode system
- Low harmonic content
- High efficiency
- Type: Single-phase alternators
- Poles: 4
- Phases: Single-phaseRegulation: CAPACITOR
- Application: PORTABLE, LIGHTING TOWERS

## **Product features:**

Phase: Single phase

Continuous power single phase (KW): 11 Continuous power single phase (KVA): 11

Frequency (Hz): 60 Voltage (V): 110 / 220 Engine rpm (rpm): 1800

Alternator: Synchronous, brushless

Poles: 4





Single-phase power (KVA): 11

Protection degree: IP21 Motor insulation class: H

Length (mm): 405 Width (mm): 270 Height (mm): 379

Brushes: No

Type of alternator: Constant Speed

Voltage regulator: Capacitor

Weight (Kg): 61.5

