

# LINZ E1S10M H Three-phase alternator 230/400V 7 kVA 50 Hz Compound



## Product description:

**E1S/2** series are three-phase 2 poles alternators with brushes and compound regulation..

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
  
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE  
product available 50 Hz and 60 Hz

## Product features:

Phase: Three phase

Continuous power three phase (KW): 5.6

Continuous power three phase (KVA): 7

Frequency (Hz): 50 / 60

Voltage (V): 230 / 400

Engine rpm (rpm): 3000

Alternator: Synchronous

Poles: 2

Single-phase power (KVA): 7

Protection degree: IP21

Motor insulation class: H

Length (mm): 294

Width (mm): 195

Height (mm): 295

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

Weight (Kg): 33.1