



## LINZ E1S13M E/2 Threephase alternator 230V/400V 27 kVA 50 Hz Compound

## **Product description:**

**E1S/2** series are three-phase 2 poles alternators with brushes and compound regulation..

## **CHARACTERISTICS**

- Possibility to feed any type of load
- · Compact and easy to assemble
- · High starting capacity
- High efficiency
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phaseRegulation: COMPOUND
- Application: PORTABLE
- product available in 50 Hz and 60 Hz versions

## **Product features:**

Phase: Three phase

Continuous power three phase (KW): 21.6 Continuous power three phase (KVA): 27

Frequency (Hz): 50 / 60 Voltage (V): 230 / 400 Engine rpm (rpm): 3000





Alternator: Synchronous

Poles: 2

Three-phase power (KVA): 27

Protection degree: IP21 Motor insulation class: H

Length (mm): 495 Width (mm): 270 Height (mm): 379 Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

Weight (Kg): 88

