

LINZ E1X13S A/2 Three-phase alternator 230V/400V 8 kVA 50 Hz AVR



Product description:

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
- Minimum maintenance
- High efficiency

- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: AVR
- Application: PORTABLE, TELECOMMUNICATION
product available in 50 Hz and 60 Hz versions

Product features:

Phase: Three phase

Continuous power three phase (KW): 6.4

Continuous power three phase (KVA): 8

Frequency (Hz): 50 / 60

Voltage (V): 230 / 400

Engine rpm (rpm): 3000
Alternator: Synchronous
Poles: 2
Single-phase power (KVA): 8
Protection degree: IP21
Motor insulation class: H
Length (mm): 465
Width (mm): 270
Height (mm): 379
Brushes: No
Type of alternator: Constant Speed
Voltage regulator: AVR
Weight (Kg): 56.5