



LINZ E1X13M D/2 Three-phase alternator 230V/400V 16 kVA 50 Hz AVR



Product description:

E1X/2 series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

CHARACTERISTICS

- Compact and mechanically resistant
 - Minimum maintenance
 - High efficiency

 - Type: Three-phase alternators
 - Poles: 2
 - Phases: Three-phase
 - Regulation: AVR
 - Application: PORTABLE, TELECOMMUNICATION
- Product available in 50 Hz and 60 Hz versions

Product features:

Phase: Three phase

Continuous power three phase (KW): 12.8

Continuous power three phase (KVA): 16

Frequency (Hz): 50 / 60

Voltage (V): 230 / 400



Engine rpm (rpm): 3000
Alternator: Synchronous
Poles: 2
Three-phase power (KVA): 16
Protection degree: IP21
Motor insulation class: H
Length (mm): 554
Width (mm): 270
Height (mm): 375
Brushes: No
Type of alternator: Constant Speed
Voltage regulator: AVR
Weight (Kg): 86