



# LINZ E1X13M D/2 Three-phase alternator 230V/400V 16 kVA 50 Hz AVR



## Product description:

**E1X/2** series are three-phase brushless 2 poles alternators with exciter and electronic regulation (AVR).

## CHARACTERISTICS

- Compact and mechanically resistant
  - Minimum maintenance
  - High efficiency
  
  - Type: Three-phase alternators
  - Poles: 2
  - Phases: Three-phase
  - Regulation: AVR
  - Application: PORTABLE, TELECOMMUNICATION
- Product available in 50 Hz and 60 Hz versions

## Product features:

Phase: Three phase

Continuous power three phase (KW): 12.8

Continuous power three phase (KVA): 16

Frequency (Hz): 50 / 60

Voltage (V): 230 / 400



---

Engine rpm (rpm): 3000  
Alternator: Synchronous  
Poles: 2  
Three-phase power (KVA): 16  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 554  
Width (mm): 270  
Height (mm): 375  
Brushes: No  
Type of alternator: Constant Speed  
Voltage regulator: AVR  
Weight (Kg): 86