



# LINZ E1S11M B KE Three-phase alternator 277V/480V 14 kVA 60 Hz AVR + Compound

## Product description:

**E1S-KE** series are three-phase 2 poles alternators with brushes and mixed regulation: compound and electronic (AVR).

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
  
- Type: Three-phase alternators
- Poles: 2
- Phases: Three-phase
- Regulation: COMPOUND AND AVR
- Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 11.2

Continuous power three phase (KVA): 14

Frequency (Hz): 60

Voltage (V): 277 / 480



---

Engine rpm (rpm): 3600  
Alternator: Synchronous  
Poles: 2  
Single-phase power (KVA): 14  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 415  
Width (mm): 230  
Height (mm): 325  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: AVR+Compound  
Weight (Kg): 51.5