

# LINZ E1S13S A/4 Three-phase alternator 4 poles 8 kVA 50 Hz Compound



## Product description:

**E1S13/4** series are three-phase 4 poles alternators with brushes and compound regulation.

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
  
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 6.4

Continuous power three phase (KVA): 8

Frequency (Hz): 50

Voltage (V): 230 / 400

---

Engine rpm (rpm): 1500  
Alternator: Synchronous  
Poles: 4  
Three-phase power (KVA): 8  
Protection degree: IP21  
Motor insulation class: H  
Length (mm): 403  
Width (mm): 270  
Height (mm): 379  
Brushes: Yes  
Type of alternator: Constant Speed  
Voltage regulator: Compound  
Weight (Kg): 51