



# LINZ E1S13M D/4 Three-phase alternator 4 poles 16 kVA 60 Hz Compound

## Product description:

**E1S13/4** series are three-phase 4 poles alternators with brushes and compound regulation.

## CHARACTERISTICS

- Possibility to feed any type of load
- Compact and easy to assemble
- High starting capacity
- High efficiency
  
- Type: Three-phase alternators
- Poles: 4
- Phases: Three-phase
- Regulation: COMPOUND
- Application: PORTABLE

## Product features:

Phase: Three phase

Continuous power three phase (KW): 12.8

Continuous power three phase (KVA): 16

Frequency (Hz): 60

Voltage (V): 277 / 480



Engine rpm (rpm): 1800

Alternator: Synchronous

Poles: 4

Three-phase power (KVA): 16

Protection degree: IP21

Motor insulation class: H

Length (mm): 403

Width (mm): 270

Height (mm): 373

Brushes: Yes

Type of alternator: Constant Speed

Voltage regulator: Compound

Weight (Kg): 70.5