



TESSARI ERLE EUW30 Silenced Generator With Manual Control Unit 33 KVA

Product description:

Product features:

Phase: Three phase

Maximum power three phase (KW): 26.4

Continuous power three phase (KW): 24

Maximum power three phase (KVA): 33

Continuous power three phase (KVA): 30

Fuel: Diesel

Frequency (Hz): 50

Voltage (V): 400

Engine: BAUDOUIN 3M10G33/5

Engine rpm (rpm): 1500

Speed governor: Mechanical

Starting system: Electric 12 Vcc

Engine capacity (cm³): 3120

Number cylinders: 3

Cylinders' position: In line

Oil capacity (L): 7.25

Alternator: LEROY SOMER TAL 042C

Poles: 4

Protection degree: IP23

Fuel tank capacity (L): 120

Consumption (L/h): 7 at 100% of the load

Running time (h): 17 at 100% of the load

Acoustic pressure: 70 dB(A) at 7 m

Length (mm): 2200

Width (mm): 1030
Height (mm): 1700
Dry weight (Kg): 1200
Silenced: Yes
Super silenced: Yes
Voltage regulator: AVR