



HONDA EU22i USED GENERATOR 2,2KW SINGLE-PHASE STAGEV INVERTER

Product description:

HONDA EU22i USED GENERATOR 2,2KW SINGLE-PHASE STAGEV INVERTER

The generator USED HONDA EU22i is equipped with a Honda GXR120 Gasoline engine capable of delivering a maximum power of 2,2 KW, complete with Inverter voltage regulator.

The Honda EU22i Inverter is compact yet contains all the necessary functions and innovations to ensure the delivery of clean and eco-friendly energy for the operation of sensitive electronic equipment in large outdoor spaces.

Thanks to the sound-absorbing coatings and the exclusive exhaust system silencer, Honda generators are the quietest. A combination of lightweight materials, ergonomic design, and a comfortable handle make this generator easy to lift and transport.

The exclusive Inverter technology of the Honda EU22i USED provides constant, clean, and uninterrupted electrical power. Introduced by Honda in 1987, it works in conjunction with a load sensing device that provides high-quality electricity based on demand, a quality that effectively matches that of household power.

Thanks to the unique ECO-Throttle™ load sensing feature, the engine speed increases with the load. This operation is automatic and instantaneous to keep up with demand. The Oil Alert™ technology will automatically shut off the engine if the oil level drops below the safety limit.

The Honda EU22i USED portable generators can be connected together using a parallel cable to double the power output. When connected, they can meet the needs of smaller setups, such as powering an air conditioner in a camper. Two smaller generators are easier to manage and transport than a larger one and, once connected on-site, can increase the power output.

A convenient 12V DC outlet allows for charging a car battery while simultaneously providing

power to other devices. These portable generators represent comprehensive energy solutions.

STAGEV EMISSIONS REGULATIONS

The generator is equipped with STAGEV "mobile" engine as required by the European Regulation 2016/1628. These new engines exponentially reduce particle and nitrogen oxide emissions from the generator into the environment, ensuring a 200% reduction in environmental impact compared to standard engines.

MANELSERVICE USED

The unit used by Manelservice guarantees that this generator has always received regular maintenance from a team of specialized technicians and is in optimal condition.

USED HONDA EU22i TECHNICAL SPECIFICATIONS

Phase Type: Single-Phase

Continuous Power: 2.25 KVA / 1.8 KW

Maximum Power: 2.75 KVA / 2.2 KW

Fuel: Gasoline

Voltage: 230 V

Frequency: 50 Hz

Engine: Honda GXR120

Engine Speed: 4000 rpm

Emissions Regulation: StageV

Starting: Manual Recoil

Voltage Regulator: Inverter

Outlet Configuration: 2 x Schuko 230V 16A

Consumption: 0.93 L/h

Tank Capacity: 3.6 L

Autonomy: 3.83 h

Sound Pressure: 72 dB(A)

Length: 512 mm

Width: 290 mm

Height: 425 mm

Weight: 20.7 Kg

Looking for a product with different technical features? [HERE](#) you can find the dedicated section for USED generators from specialized brands.

Images and technical data are indicative, the color of the unit may vary based on availability.

**Product features:**

Phase: Single phase

Maximum power single phase (KW): 2.2

Continuous power single phase (KW): 1.8

Maximum power single phase (KVA): 2.75

Continuous power single phase (KVA): 2.25

Fuel: Gasoline

Frequency (Hz): 50

Voltage (V): 230

Sockets configuration: 2 x 230V SCHUKO

Engine: Honda GXR120, 4 stroke, OHV

Emissions Regulations: Stage 5

Engine rpm (rpm): 4000

Ignition: Transistorized

Starting system: Recoil

Engine capacity (cm³): 121

Number cylinders: 1

Oil capacity (L): 0.4

Cooling: Forced air

Alternator: Multipolar

Bore x stroke (mm): 60 x 43

Fuel tank capacity (L): 3.6

Consumption (L/h): 0.93

Running time (h): 3.83

Acoustic power: 90 dB(A)

Acoustic pressure: 72 dB(A)

Length (mm): 512

Width (mm): 290

Height (mm): 425

Dry weight (Kg): 20.7

Inverter: Yes

AVR: No

Compound: No

Silenced: Yes

Super silenced: Yes

