



# GENMAC GAMMA-GAS G60GO-NG THREE- PHASE 56 KVA NATURAL GAS - STAMFORD ALTERNATOR

## Product description:

The INDUSTRIAL power generator range also includes a Gas-powered series (Natural Gas / LPG) from 30 to 100 KVA and a series with air cooled engine from 30 to 100 KVA.

Genmac Industrial range diesel generating sets are used worldwide in different application fields and supply current to Hospitals, Industries, Shopping centres, Hotels, Hen houses, Data centres, Mills, Airports, Fish farms, Events, Resorts, GSM towers, Banks, Universities, Stadiums, and Offices.

Not binding images and technical data.

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 48

Continuous power three phase (KW): 45

Maximum power three phase (KVA): 60

Continuous power three phase (KVA): 56

Fuel: Natural Gas

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: Terminal box

Engine: General Motors RMG5700-D01-01

Emissions Regulations: Stationary Use

Engine rpm (rpm): 1500

Speed governor: Electronic



---

Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 5700  
Number cylinders: 8  
Oil capacity (L): 4.7  
Cooling: Water  
Alternator: Stamford S1L2-Y1, self-excited  
Poles: 4  
Natural Gas consumption (m<sup>3</sup>/h): 18.1  
Length (mm): 2250  
Width (mm): 1020  
Height (mm): 1538  
Dry weight (Kg): 1004  
Silenced: No  
Super silenced: No  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: General Motors