



GENMAC QUEEN-GAS G85GS-NG THREE- PHASE 79 KVA NATURAL GAS - MECC ALTE ALTERNATOR

Product description:

GENMAC QUEEN-GAS G85GS-NG

The GENMAC QUEEN-GAS G85GS-NG is a 79 KVA super-silenced single-phase/three-phase NG generator set with Mecc Alte alternator and AVR voltage regulator.

Thanks to its natural gas fuel supply, the GENMAC QUEEN-GAS G85GS-NG can only consume 26.3 Lt/h at full load and has a low environmental impact, making it one of the best in its class.

The long life and reliability of the GENMAC QUEEN-GAS G85GS-NG is due to a special control procedure during the various stages of production.

The GENMAC QUEEN-GAS G85GS-NG is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

Images and technical data are not binding.

Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 75

Continuous power three phase (KW): 63

Maximum power three phase (KVA): 93

Continuous power three phase (KVA): 79

Fuel: Natural Gas

Frequency (Hz): 50

Voltage (V): 230 / 400

Sockets configuration: Terminal box



Engine: General Motors RMG8000-D01-01

Emissions Regulations: Stationary Use

Engine rpm (rpm): 1500

Speed governor: Electronic

Starting system: Electric

Engine capacity (cm³): 8000

Number cylinders: 8

Oil capacity (L): 7.6

Cooling: Water

Alternator: Mecc Alte ECP34-1S/4A, self-excited

Natural Gas consumption (m³/h): 28.4

Width (mm): 1056

Height (mm): 1900

Dry weight (Kg): 1500

Silenced: Yes

Super silenced: Yes

ATS Switch device : No

Voltage regulator: AVR

Engine manufacturer: General Motors

