



# GENMAC QUEEN-GAS G105GS GPL THREE- PHASE 100 KVA - STAMFORD ALTERNATOR

## Product description:

### GENMAC QUEEN-GAS G105GS-GPL

The GENMAC QUEEN-GAS G105GS-GPL is a 100 KVA super-silenced single-phase/three-phase GPL generator set with Stamford alternator and AVR voltage regulator.

Thanks to its natural gas fuel supply, the GENMAC QUEEN-GAS G105GS-GPL can only consume 44.3 Lt/h at full load and has a low environmental impact, making it one of the best in its class.

The long life and reliability of the GENMAC QUEEN-GAS G105GS-GPL is due to a special control procedure during the various stages of production.

The GENMAC QUEEN-GAS G105GS-GPL is suitable for applications in different contexts such as: hospitals, industries, shopping malls, hotels, airports, banks, universities, stadiums, offices, etc.

Images and technical data are not binding.

## Product features:

Phase: Single phase / Three phase

Maximum power three phase (KW): 88

Continuous power three phase (KW): 80

Maximum power three phase (KVA): 110

Continuous power three phase (KVA): 100

Fuel: LPG

Frequency (Hz): 50

---

Voltage (V): 230 / 400  
Sockets configuration: Terminal box  
Engine: General Motors RMG8800-D51-01  
Emissions Regulations: Stationary Use  
Engine rpm (rpm): 1500  
Speed governor: Electronic  
Starting system: Electric  
Engine capacity (cm<sup>3</sup>): 8800  
Number cylinders: 8  
Oil capacity (L): 7.57  
Cooling: Water  
Alternator: Stamford UCI274C, self-excited  
LPG consumption (L/h): 44.3  
Width (mm): 1056  
Height (mm): 1900  
Dry weight (Kg): 1500  
Silenced: Yes  
Super silenced: Yes  
Product type: Generator  
ATS Switch device : No  
Voltage regulator: AVR  
Engine manufacturer: General Motors